Kalpana: Resonant Interference Memory

A Constant-State Neural Architecture for Long-Context Sequence Modeling via Phase-Coded Holographic Dynamics

Anonymous Authors

Paper under double-blind review

Abstract

The fundamental bottleneck in scaling Transformer-based sequence models is the growth of explicit context memory—the $O(N)$ KV-cache that scales linearly with sequence length. This paper presents **Kalpana**, a neural architecture centered on the **Resonant Interference Field (RIF)**, a constant-state memory substrate that encodes temporal information through phase-coded superposition in complex Hilbert space. Unlike token-indexed systems that allocate new memory for each token, Kalpana maintains a fixed-size state $S \in \mathbb{C}^{B \times D}$, enabling $O(1)$ memory scaling independent of sequence length.

Kalpana operates in two complementary modes: (1) as a **standalone external memory substrate** for existing models, where documents are embedded into the RIF and retrieved at query time without modifying the downstream model, demonstrating constant 6 MiB memory across contexts up to 100K+ tokens with 86–100% retrieval fidelity and >9,000× memory reduction at 1M tokens relative to Transformer KV-cache scaling; and (2) as a **native internal KV-cache replacement (Paradigm A)**, where Key-Value tensors are projected into a continuous Fourier phase state, demonstrating native compatibility with Rotary Positional Embeddings (RoPE) and Grouped-Query Attention (GQA) with a constant **48.00 MB** state across 3,000,000 tokens.

We derive the **Unified Spectral Packing Law** $N_{\text{tokens_limit}} \approx \Gamma \cdot B$, showing that capacity is governed by phase-space crowding ($\Gamma \approx 1{,}465$ tokens per band, yielding 3,000,000 tokens for $B = 2{,}048$) rather than memory exhaustion, establishing a single physical law for both external memory and internal KV-cache replacement. These results establish Kalpana as a practical and theoretical foundation for memory-efficient AI systems capable of long-context reasoning under strict hardware constraints.

1 Introduction

1.1 The Memory Wall in Modern Sequence Models

Modern sequence modeling is at a crossroads. The Transformer architecture, introduced by Vaswani et al. [1], has become the dominant paradigm for natural language processing and beyond. Its core innovation—the attention mechanism—provides unparalleled representational power by allowing each token to attend to all previous tokens in the sequence. However, this power comes at a fundamental cost: the Key-Value (KV) cache must store representations for every token in the context window.

Let N be the sequence length, d_{model} the model dimension, and n_{layers} the number of layers. The KV-cache memory footprint scales as:

$$M_{\text{KV}} = 2 \times N \times d_{\text{model}} \times n_{\text{layers}} \times \text{bytes-per-element} \quad (1)$$

For a model such as Qwen 2.5 7B (28 layers, 4 GQA KV-heads, $d_{\text{head}} = 128$, FP16):

- At $N = 128$K: $M_{\text{KV}} \approx 2 \times 128{,}000 \times 4 \times 128 \times 28 \times 2 \approx 7$ GB
- At $N = 1$M: $M_{\text{KV}} \approx 55$ GB

These memory requirements exceed single-node GPU capacity, forcing complex distributed inference or aggressive context truncation that sacrifices long-range dependencies.

1.2 Biological Inspiration: Memory as Interference

In biological systems, memory does not expand linearly with every second of sensory input. The human brain maintains approximately 2.5×10^{15} synapses within a fixed volume of approximately 1.2 liters. New memories

Reviewers: please read the Reviewer Guidelines (iclr.cc/Conferences/2027/ReviewerGuidelines) and the AI Policy for Reviewers (iclr.cc/Conferences/2027/AIPolicyForReviewers). If you used AI to expand, edit, or polish your review, please provide the input text to the LLM. Better still, consider skipping the LLM and submitting your original text: we, and the authors, are much more interested in your unedited thoughts than in what an LLM has to say. AI-assisted or not, you are putting your name and reputation behind your review: LLM-generated falsehoods, hallucinations or misrepresentations are subject to disciplinary action, which may include desk-rejecting all papers you have authored.

are integrated into existing neural structures through mechanisms of synaptic plasticity and pattern completion, not by allocating new neurons for each experience [9].

This observation motivates a fundamental question: *Can artificial memory systems be designed that maintain constant physical footprint while supporting indefinite sequence lengths?*

1.3 Contributions of This Work

This paper introduces **Kalpana**, a neural architecture that reimagines memory as a continuous **Resonant Interference Field (RIF)**. The contributions include:

1. **A Novel Memory Architecture**: Kalpana replaces the linear KV-cache with a fixed-size complex-valued state tensor $S \in \mathbb{C}^{B \times D}$, where B is the number of frequency bands and D is the feature dimension. Memory footprint is $O(1)$ with respect to sequence length.
2. **Phase-Coded Temporal Encoding**: Information is stored via superposition, with temporal position encoded through phase rotation $\theta = \kappa\omega t$. This leverages the orthogonality properties of complex exponentials to minimize interference.
3. **The Unified Spectral Packing Law**: A theoretical bound on total token capacity is derived: $N_{\text{tokens_limit}} \approx \Gamma \cdot B$, where $\Gamma \approx 1{,}465$ is the spectral band load factor (tokens per band). For $B = 2{,}048$ frequency bands and $D = 3{,}072$, the RIF natively stores up to $N \approx 3{,}000{,}000$ tokens inside a constant 48.00 MB memory state without any token aggregation or chunking.
4. **Empirical Validation**: Through extensive stress testing across scales from 128K to 6.6M tokens, 100% retrieval fidelity is demonstrated within capacity limits and the exact point of phase collapse at $N_{\text{tokens}}/B \approx 2{,}930$ (tokens per band) is quantified.
5. **Hardware-Efficient Implementation**: Kalpana achieves a 1,167× memory reduction at 128K context and >9,000× reduction at 1M context compared to Transformer baselines (Qwen 2.5 7B, FP16), enabling long-context inference on consumer GPUs.
6. **Native Drop-In Attention for Pretrained Models (Paradigm A)**: We formulate and validate a native replacement for 'LlamaAttention' that harmonizes continuous Fourier phase modulation with spatial Rotary Positional Embeddings (RoPE) and Grouped-Query Attention (GQA), maintaining a constant 48.00 MB state across 3,000,000 tokens with 100% Multi-Query Associative Recall (MQAR).

1.4 Decoupling Memory from Reasoning

Contemporary neural architectures tightly couple memory storage and reasoning within a single computational framework. In Transformer-based systems, this coupling manifests as the KV cache, which simultaneously serves as both storage and retrieval mechanism. This design introduces a fundamental limitation, as memory usage scales linearly with sequence length.

Kalpana introduces an alternative paradigm in which memory is externalized into a dedicated substrate. In this formulation:

- Memory is represented as a constant-state interference field
- Retrieval is performed through phase-conjugate decoding
- Reasoning is performed by a separate model architecture

This separation yields several advantages:

- Memory requirements become independent of sequence length
- Existing models can integrate the memory substrate without architectural modification
- Long-context reasoning becomes feasible under bounded resource constraints

Accordingly, Kalpana may be interpreted not only as a novel neural architecture, but as a general-purpose memory primitive for artificial intelligence systems.

2 Mathematical Foundations of Resonant Interference Memory

2.1 Interference-Based Memory Representation

Kalpana represents memory as a superposition of complex-valued embeddings within a fixed-dimensional Hilbert space. Each input token x_t is mapped to an embedding vector $V_t \in \mathbb{R}^D$, which is written into a multi-band interference field. Rather than allocating separate memory slots for each token, all contributions are accumulated into a constant-size state.

The most general form of the memory state is defined as:

$$S_t = \sum_{k=0}^{t} \gamma^k \, e^{i(\kappa \Omega k + \Phi_{\text{init}})} \odot V_{t-k} \tag{2}$$

where:

- $\gamma \in (0, 1]$ is a retention factor controlling temporal decay,
- κ is a phase scaling constant,
- $\Omega \in \mathbb{R}^B$ is a vector of angular frequencies,
- $\Phi_{\text{init}} \in [0, 2\pi)^B$ is a vector of **initial phase offsets**, drawn independently and uniformly at random for each band during initialization,

- $\odot$ denotes element-wise modulation across frequency bands.

Remark 1 (Implementation Defaults). The initial phase offsets Φ_{init} serve a critical practical role: they break the phase degeneracy at position $t = 0$, where all bands would otherwise share the same zero phase angle. Without these offsets, all bands produce identical phasor values at $t = 0$, concentrating the stored energy into a narrow region of phase space and degrading retrieval of early tokens. By randomizing the initial phases, the system distributes stored contributions more uniformly across the complex plane from the very first write.

In the current reference implementation (see Section 7.1), the retention factor is set to $\gamma = 1.0$ (no temporal decay). This choice maximizes total recall by treating all past tokens equally. The framework supports $\gamma < 1$ for applications requiring recency-weighted memory, but all empirical results reported in this paper use $\gamma = 1.0$.

This formulation enables constant-state memory, in which temporal information is encoded through phase rather than explicit storage.

2.2 Band-wise Formulation

For each frequency band b, the memory state evolves as:

$$S_t^{(b)} = \sum_{k=0}^{t} \gamma^k \, e^{i(\kappa \omega_b k + \phi_{\text{init}}^{(b)})} \, V_{t-k} \tag{3}$$

where $\phi_{\text{init}}^{(b)} \sim \mathcal{U}(0, 2\pi)$ is the initial phase offset for band b. Each band acts as a resonant accumulator, storing temporally shifted contributions with phase rotation. The full state is given by:

$$S_t = \left[S_t^{(1)}, S_t^{(2)}, \ldots, S_t^{(B)} \right] \tag{4}$$

2.3 Why Complex Phase Enables Constant-State Memory

In real-valued summation, multiple stored vectors interfere destructively without a mechanism for separation. Complex phase encoding introduces a temporal signature:

$$V_t \mapsto V_t \, e^{i(\kappa \omega_b t + \phi_{\text{init}}^{(b)})} \tag{5}$$

This phase structure allows multiple temporal contributions to coexist within the same state while remaining partially recoverable through phase alignment.

2.4 Retrieval via Phase-Conjugate Projection

Retrieval is performed using a phase-conjugate probe:

$$P_t^{(b)} = e^{-i\kappa\omega_b t} \tag{6}$$

The retrieved signal is:

$$Z_t = \sum_{b=1}^{B} S^{(b)} \, P_t^{(b)} \tag{7}$$

and the reconstructed output is:

$$\hat{V}_t = \Re(Z_t) \tag{8}$$

Substituting the memory definition:

$$Z_t = \sum_{b=1}^{B} \sum_{\tau=0}^{N} \gamma^\tau V_{N-\tau} e^{i\kappa\omega_b \tau} e^{-i\kappa\omega_b t} \tag{9}$$

$$= \sum_{\tau=0}^{N} \gamma^\tau V_{N-\tau} \sum_{b=1}^{B} e^{i\kappa\omega_b(\tau - t)} \tag{10}$$

When $\tau = t$, the contributions align coherently across bands, while other terms interfere destructively.

2.5 Signal and Interference Analysis

The retrieved signal can be decomposed into:

$$\hat{V}_t = B V_t + \sum_{\tau \neq t} V_\tau \sum_{b=1}^{B} e^{i\kappa\omega_b(\tau - t)} \tag{11}$$

This leads to an approximate signal-to-noise ratio:

$$\text{SNR} \sim \frac{B}{\sqrt{N}} \tag{12}$$

Defining band load $\Gamma = N/B$:

$$\text{SNR} \sim \sqrt{\frac{B}{\Gamma}} \tag{13}$$

2.6 Direct Phase Decoding

The retrieval formulation described above can be interpreted as a spectral decoding process. Rather than performing sequential probing over possible delays, the interference field permits direct reconstruction of temporal components through phase-conjugate projection.

Given a memory state:

$$S_b = \sum_{t=1}^{N} V_t e^{i\kappa\omega_b t} \tag{14}$$

a time-resolved signal can be reconstructed as:

$$f(t) = \Re \left(\sum_{b=1}^{B} S_b e^{-i\kappa\omega_b t} \right) \tag{15}$$

This formulation is analogous to an inverse spectral transform, where temporal information is recovered directly from the phase structure of the interference field.

Importantly, this enables:

- Direct retrieval without explicit iteration over time indices
- Parallel decoding of multiple temporal components
- Efficient implementation via FFT-like algorithms

Thus, the Kalpana memory substrate supports both probe-based retrieval and direct spectral decoding, with the latter providing a more efficient and physically grounded interpretation of the recall process.

2.7 Spectral Packing and Capacity

The storage capacity is governed by phase-space crowding rather than explicit memory size. The RIF state updates on every incoming token embedding vector $\mathbf{x}_t \in \mathbb{R}^D$. Let N_{tokens} denote the total number of tokens accumulated in the RIF state. The maximum sequence length before phase collapse is:

$$N_{\text{tokens_limit}} = \Gamma \cdot B \tag{16}$$

where B is the number of frequency bands, and $\Gamma \approx 1{,}465$ is the **spectral band load factor** (tokens per band at the stability threshold). For $B = 2{,}048$ frequency bands and $D = 3{,}072$ model dimension, the constant RIF memory footprint is:

$$M_{\text{RIF}} = 2{,}048 \times 3{,}072 \times 8 \text{ bytes} = 48.00 \text{ MB} \tag{17}$$

which natively supports up to $N = 3{,}000{,}000$ tokens without any requirement for token aggregation or chunking.

2.8 Role of κ

The complete phase encoding function is:

$$\phi(b, t) = \kappa \omega_b t + \phi_{\text{init}}^{(b)} \tag{18}$$

where $\phi_{\text{init}}^{(b)}$ is the per-band initial phase offset. The scaling factor κ controls temporal encoding:

- small κ reduces separability
- large κ increases aliasing
- intermediate κ balances resolution and capacity

2.9 Band Load and the Kalpana Limit

Define the spectral band load factor as the number of phase snapshots per frequency band:

$$\Gamma = \frac{N_{\text{snapshots}}}{B} \tag{19}$$

where $N_{\text{snapshots}}$ is the total number of vectors written to the RIF state. Γ is a pure phase-space quantity; it does not depend on what the caller chooses each snapshot to represent. Stable operation requires:

$$\Gamma \lesssim \frac{B}{\tau^2} \tag{20}$$

Empirically:

$$\Gamma \approx 10\text{–}15 \quad \text{(snapshots per band)} \tag{21}$$




Figure 1: Architecture of the Resonant Interference Field (RIF). Tokens are encoded with position-dependent phase rotations and accumulated into a fixed-size complex state S. Retrieval uses phase conjugation to extract the desired token.

2.10 Simultaneous Multi-Point Retrieval

Multiple time points may be retrieved simultaneously:

$$P = \sum_{k=1}^{K} e^{-i\kappa\omega_b t_k} \tag{22}$$

$$\hat{V} = \Re\left(\sum_b S[b] \cdot P\right) \tag{23}$$

with approximate scaling:

$$\text{SNR} \sim \frac{B}{\sqrt{N + K}} \tag{24}$$

2.11 Interpretation as a Resonant Field

Kalpana may be interpreted as a resonant memory field in which information is encoded through phase relationships rather than spatial storage. Retrieval corresponds to phase alignment, linking the model to physical interference systems and enabling constant-state memory representations.

3 The Resonant Interference Field (RIF): Architecture and Operation

3.1 Conceptual Overview

The Resonant Interference Field (RIF) is a memory substrate that stores information through wave interference rather than discrete storage slots. Figure 1 presents a comprehensive view of the RIF architecture.

3.2 Detailed Operation of the RIF

The RIF operates through three fundamental stages: **Encoding**, **Storage**, and **Retrieval**.

3.2.1 Stage 1: Encoding (Write Operation)

When a token arrives at position t, its feature vector $\mathbf{x}_t$ undergoes a phase encoding transformation:

$$\mathbf{z}_t(b) = \mathbf{x}_t \odot e^{i\kappa\omega_b t} = \mathbf{x}_t \cdot (\cos(\kappa\omega_b t) + i \sin(\kappa\omega_b t)) \tag{25}$$

This operation rotates each dimension of $\mathbf{x}_t$ by the same phase angle $\phi(b,t) = \kappa\omega_b t$. The key insight is that the phase rotation is *position-dependent* and *band-dependent*, creating a unique signature for each (t, b) pair.

Property 1 (Orthogonality Across Positions). For two different positions t_1 and t_2, the expected inner product between their encoded representations across all bands is:

$$\mathbb{E}\left[\sum_{b=0}^{B-1}\langle \mathbf{x}_{t_1} e^{i\phi(b,t_1)}, \mathbf{x}_{t_2} e^{i\phi(b,t_2)}\rangle\right] \approx \frac{1}{\sqrt{B}}\langle \mathbf{x}_{t_1}, \mathbf{x}_{t_2}\rangle \quad (26)$$

This interference suppression factor $1/\sqrt{B}$ enables superposition without catastrophic interference.

3.2.2 Stage 2: Storage (State Accumulation)

The encoded vectors are added to the RIF state S:

$$S[b] \leftarrow S[b] + \mathbf{z}_t(b) \quad (27)$$

After storing N tokens, the state becomes:

$$S[b] = \sum_{t=1}^{N} \mathbf{x}_t e^{i\kappa\omega_b t} \quad (28)$$

This is the core of the interference memory: a single complex matrix S contains all stored information, with each token's contribution rotated by a unique phase.

3.2.3 Stage 3: Retrieval (Read Operation)

To retrieve the token at position t, Kalpana performs phase-conjugate readout:

$$\hat{\mathbf{x}}_t = \mathrm{Re}\left(\sum_{b=0}^{B-1} S[b] \cdot e^{-i\kappa\omega_b t}\right) \quad (29)$$

Expanding this expression:

$$\hat{\mathbf{x}}_t = \mathrm{Re}\left(\sum_b \sum_{t'} \mathbf{x}_{t'} e^{i\kappa\omega_b t'} \cdot e^{-i\kappa\omega_b t}\right) \quad (30)$$

$$= \mathrm{Re}\left(\mathbf{x}_t \sum_b 1 + \sum_{t'\neq t} \mathbf{x}_{t'} \sum_b e^{i\kappa\omega_b(t'-t)}\right) \quad (31)$$

$$= B\mathbf{x}_t + \sum_{t'\neq t} \mathbf{x}_{t'} \cdot \mathrm{Re}\left(\sum_b e^{i\kappa\omega_b \Delta t}\right) \quad (32)$$

The interference term $\mathrm{Re}\left(\sum_b e^{i\kappa\omega_b \Delta t}\right)$ approximates a random walk with magnitude $\sqrt{B}$, leading to the SNR scaling derived in Section 6.

3.3 The Problem with Traditional Memory

Before presenting the Kalpana architecture, it is essential to understand why traditional approaches fail for long contexts and how interference-based memory offers a fundamentally different solution.

Traditional Memory (KV-Cache): In a Transformer, each token t stores its Key and Value vectors separately:

$$\mathrm{Memory}(t) = (\mathbf{k}_t, \mathbf{v}_t) \in \mathbb{R}^{2d} \quad (33)$$

For N tokens, total memory is $2Nd$. This is analogous to writing each fact on a separate piece of paper and storing all papers in a filing cabinet.

Problem: The filing cabinet grows linearly with the number of facts.

Interference-Based Memory (Kalpana): Instead of storing each fact separately, Kalpana adds them together using phase-coded superposition:

$$S = \sum_{t=1}^{N} \mathbf{x}_t \odot e^{i\theta_t} \quad (34)$$

where $\odot$ denotes element-wise multiplication and $e^{i\theta_t}$ is a complex phasor. This is analogous to writing all facts on a single transparency, but encoding each fact with a unique color. When light shines through, each fact can be recovered by filtering for its specific color.

Example 1 (Analogy: Orchestra vs. Solo Recordings). Consider storing the sound of an orchestra. A traditional approach would record each instrument separately (violin track, cello track, etc.), requiring storage proportional to the number of instruments. In contrast, an orchestra performs simultaneously—all instruments play together, creating a single acoustic waveform. Yet a listener can still focus on the violin melody because each instrument occupies a distinct frequency range. Kalpana operates similarly: it creates a single "waveform" (the state S) that contains all facts superimposed, but each fact occupies a unique phase-frequency "signature" that enables selective retrieval.

3.4 Complex Numbers as Memory Carriers

To understand Kalpana, one must first grasp why complex numbers are essential for interference-based memory.

3.4.1 Real Numbers: The Problem of Linear Superposition

In standard neural networks, memory is represented as real vectors. Adding two real vectors:

$$\mathbf{s} = \mathbf{v}_1 + \mathbf{v}_2 \quad (35)$$

Given only $\mathbf{s}$, it is mathematically impossible to recover $\mathbf{v}_1$ or $\mathbf{v}_2$ uniquely. There are infinitely many pairs $(\mathbf{v}_1, \mathbf{v}_2)$ that sum to $\mathbf{s}$. This is the fundamental limitation of real-valued superposition.

3.4.2 Complex Numbers: Encoding via Phase

Complex numbers extend real numbers with an imaginary component, written as $z = a + ib$ where $i = \sqrt{-1}$. A complex number can also be represented in polar form:

$$z = re^{i\theta} = r(\cos\theta + i\sin\theta) \quad (36)$$

where r is the magnitude and θ is the phase angle.

The key insight is that multiplication by $e^{i\theta}$ rotates the phase without changing magnitude:

$$z \cdot e^{i\phi} = re^{i(\theta+\phi)} \tag{37}$$

This rotation property enables *phase encoding*: each fact can be associated with a unique phase angle, allowing them to be superimposed and later separated.

Definition 1 (Complex Vector Space)**.** A complex vector $\mathbf{v} \in \mathbb{C}^D$ consists of D complex numbers. The inner product between two complex vectors is defined as:

$$\langle \mathbf{v}, \mathbf{w} \rangle = \sum_{d=1}^{D} v_d \overline{w_d} \tag{38}$$

where $\overline{w_d}$ denotes complex conjugation. This inner product respects the geometry of the complex plane.

3.5 Phase Encoding of Temporal Position

The core mechanism of Kalpana is encoding temporal position t into a phase angle $\phi(b, t)$ for each frequency band b.

3.5.1 The Encoding Function

For a token at position t, with feature vector $\mathbf{x} \in \mathbb{R}^D$, the phase-encoded representation is:

$$\mathbf{z}_t(b) = \mathbf{x} \cdot e^{i\phi(b,t)} \tag{39}$$

where:

$$\phi(b, t) = \kappa \cdot \omega_b \cdot t \tag{40}$$

- κ: Resonance scaling factor (controls how quickly phase changes with t)
- ω_b: Base frequency for band b (unique per band)
- t: Token position (integer)

Example 2 (Numerical Example). Suppose $\kappa = 10$, $\omega_b = 0.5$, and $t = 100$. Then:

$$\phi = 10 \times 0.5 \times 100 = 500 \text{ radians} \tag{41}$$

Since $e^{i\theta}$ is periodic with period 2π, this effectively encodes position modulo $2\pi/\kappa\omega_b$. Different ω_b values create different periodicities, creating a unique signature for each t across bands.

3.5.2 Why Multiple Frequency Bands?

Using a single frequency ω would create ambiguity: positions t and $t + \frac{2\pi}{\kappa\omega}$ would have identical phase. This is known as *phase wrapping*. By using B different frequencies $\omega_0, \omega_1, \ldots, \omega_{B-1}$, Kalpana creates a *multi-frequency fingerprint* for each position.

Mathematically, the vector of phases across bands:

$$\mathbf{\Phi}(t) = [\phi(0, t), \phi(1, t), \ldots, \phi(B-1, t)] \tag{42}$$

acts as a unique identifier for each t up to a maximum position determined by the frequency spacing.

Algorithm 1 Write Operation (Conceptual)

Input: Feature vector $\mathbf{x} \in \mathbb{R}^D$, position t
Output: Updated memory state S
for each frequency band $b = 0$ to $B - 1$ **do**
    Compute phase: $\phi = \kappa \cdot \omega_b \cdot t$
    Create phasor: $p = \cos\phi + i \sin\phi$
    Encode: $\mathbf{z} = \mathbf{x} \cdot p$ (broadcast across all dimensions)
    Update: $S[b] \leftarrow S[b] + \mathbf{z}$
end for

Algorithm 2 Read Operation (Conceptual)

Input: Position t, memory state S
Output: Retrieved feature vector $\hat{\mathbf{x}}$
$\mathbf{r} \leftarrow \mathbf{0} \in \mathbb{R}^D$
for each frequency band $b = 0$ to $B - 1$ **do**
    Compute phase: $\phi = \kappa \cdot \omega_b \cdot t$
    Extract real part: $\mathbf{r} \leftarrow \mathbf{r} + \text{Re}(S[b] \cdot e^{-i\phi})$
end for
$\hat{\mathbf{x}} \leftarrow \mathbf{r}/\|\mathbf{r}\|_2$ ▷ Normalize

Property 2 (Uniqueness of Phase Fingerprint). For positions $t_1 \neq t_2$, the probability that $\mathbf{\Phi}(t_1) = \mathbf{\Phi}(t_2)$ modulo 2π is zero for continuously distributed ω_b. For discretely spaced ω_b, collisions occur only when $t_1 - t_2$ is a multiple of the least common multiple of all periods, which grows exponentially with B.

3.6 The Write Operation: Storing Information

When a token arrives at position t, it undergoes the following transformation:

Intuition: Each feature dimension of $\mathbf{x}$ is multiplied by the same phasor p, rotating the entire vector in complex space. This rotated vector is added to the state for band b. After many writes, $S[b]$ becomes a sum of many rotated vectors:

$$S[b] = \sum_t \mathbf{x}_t e^{i\kappa\omega_b t} \tag{43}$$

3.7 The Read Operation: Retrieving Information


To retrieve the token stored at position t, Kalpana performs a *phase-conjugate read*:

3.7.1 Why Phase Conjugation Works

Consider what happens when reading position t from a state that contains many stored tokens:

$$\text{Re}(S[b] \cdot e^{-i\phi(b,t)}) = \text{Re}\left(\sum_{t'} \mathbf{x}_{t'} e^{i\phi(b,t')} \cdot e^{-i\phi(b,t)}\right) \tag{44}$$

$$= \text{Re}\left(\mathbf{x}_t + \sum_{t' \neq t} \mathbf{x}_{t'} e^{i(\phi(b,t') - \phi(b,t))}\right) \tag{45}$$



Complex plane representation of the RIF. Stored tokens (blue, green, red) at different phase angles sum to state $S[b]$ (orange). Reading at angle ϕ_1 projects onto that direction, recovering the blue component.

Figure 2: Complex plane representation showing phasor superposition.

The desired term $\mathbf{x}_t$ appears without any phase factor because $e^{i\phi(b,t)} \cdot e^{-i\phi(b,t)} = 1$. The interference terms are multiplied by $e^{i\Delta\phi}$ where $\Delta\phi = \kappa\omega_b(t' - t)$. When summed over b, these terms tend to cancel out if the phases are sufficiently diverse.

3.7.2 Geometric Interpretation

In the complex plane, each stored token corresponds to a vector at a specific angle. The state $S[b]$ is the vector sum of all these vectors. Reading at position t projects this sum onto the direction of $e^{-i\phi(b,t)}$, effectively measuring how much energy is aligned with that specific phase.

3.8 Why Superposition Works: The Orthogonality Argument

The success of Kalpana relies on the approximate orthogonality of different phase-encoded vectors.

Definition 2 (Approximate Orthogonality)**.** Two phase-encoded vectors $\mathbf{x}e^{i\phi_1}$ and $\mathbf{y}e^{i\phi_2}$ are approximately orthogonal if their inner product is small:

$$\langle \mathbf{x}e^{i\phi_1}, \mathbf{y}e^{i\phi_2} \rangle = \langle \mathbf{x}, \mathbf{y} \rangle \cdot e^{i(\phi_2 - \phi_1)} \tag{46}$$

For random $\mathbf{x}, \mathbf{y}$, the expected magnitude is $|\langle \mathbf{x}, \mathbf{y} \rangle| \approx 1/\sqrt{D}$. The phase factor does not affect the magnitude.

The key is that when summing over multiple frequency bands b, the contributions from different positions tend to interfere destructively:

Lemma 1 (Destructive Interference)**.** *For $t' \neq t$, the sum over bands:*

$$\frac{1}{B} \sum_{b=0}^{B-1} e^{i\kappa\omega_b(t'-t)} \tag{47}$$

has expected magnitude $\approx 1/\sqrt{B}$ for uniformly distributed ω_b, leading to an interference suppression factor of $1/\sqrt{B}$.

3.9 Memory Capacity: The Fundamental Trade-off

The capacity of Kalpana is governed by the *signal-to-noise ratio* (SNR):

$$\text{SNR} \approx \frac{D}{1 + \frac{N}{B}} \tag{48}$$

This reveals the fundamental trade-off:

- Increasing dimension D improves SNR linearly
- Increasing bands B improves SNR linearly
- Storing more tokens N reduces SNR inversely

The Kalpana Limit $N/B \approx 12$ represents the point where the interference term becomes comparable to the signal.

3.10 The Role of κ: Temporal Phase Scaling and Capacity Control

A central parameter governing the behavior of the Resonant Interference Field is the phase scaling factor κ, defined through:

$$\phi(b,t) = \kappa \cdot \omega_b \cdot t \tag{49}$$

κ controls how discrete time is embedded into continuous phase space. It therefore determines the *geometry of memory encoding.*

3.10.1 Operational Regimes of κ

- **Small κ:** insufficient phase separation $\rightarrow$ interference dominates
- **Large κ:** rapid phase wrapping $\rightarrow$ aliasing across time
- **Optimal κ:** maximizes separability while avoiding collisions

3.10.2 Capacity Relationship

From the Spectral Packing Law, the snapshot capacity scales as:

$$N_{\text{snapshots_limit}} \approx \frac{2\pi D}{\kappa\sigma_\omega} \tag{50}$$

and total token capacity is $N_{\text{tokens_limit}} = N_{\text{snapshots_limit}} \times C = 12.21 \times B \times C$.

Thus:

- $\kappa \uparrow \rightarrow$ phase density increases
- $\rightarrow$ interference increases
- $\rightarrow$ capacity decreases

Key Principle:

κ defines the trade-off between temporal resolution and memory capacity.

3.11 Origin of the Kalpana Limit $\Gamma \approx 12$

Define:

$$\Gamma = \frac{N}{B} \tag{51}$$

Empirically, stable retrieval occurs at:

$$\Gamma \approx 12 \tag{52}$$

3.11.1 Signal vs Noise Analysis

From retrieval expansion:

$$\hat{x}_t = Bx_t + \sum_{t' \neq t} x_{t'} \cdot \sum_b e^{i\kappa\omega_b(t'-t)} \tag{53}$$

We identify:

- Signal $\sim B$
- Noise $\sim \sqrt{N}$

Thus:

$$\text{SNR} \sim \frac{B}{\sqrt{N}} = \sqrt{\frac{B}{\Gamma}} \tag{54}$$

Stable retrieval requires SNR $> \tau$:

$$\Gamma \lesssim \frac{B}{\tau^2} \tag{55}$$

For cosine similarity:

$$\tau \approx 0.3 - 0.4 \Rightarrow \Gamma \approx 10 - 15 \tag{56}$$

Matches observed behavior:

- $\Gamma \approx 12 \rightarrow$ stable (100%)
- $\Gamma \approx 24 \rightarrow$ degradation
- $\Gamma > 40 \rightarrow$ collapse

Conclusion: the Kalpana limit emerges from interference statistics.

3.12 Simultaneous Retrieval and Multi-Point Resonance

A unique capability of Kalpana is simultaneous multi-position retrieval.

3.12.1 Multi-Target Probe

$$P = \sum_{k=1}^{K} e^{-i\kappa\omega_b t_k} \tag{57}$$

$$\hat{x} = \text{Re}\left(\sum_b S[b] \cdot P\right) \tag{58}$$

Expands to:

$$\hat{x} = \sum_{k=1}^{K} Bx_{t_k} + \text{interference} \tag{59}$$




Figure 3: SNR decreases as tokens per band increase. Stability collapses near $\Gamma \approx 12$.

3.12.2 Interpretation

- multiple targets retrieved in parallel
- signals add coherently
- noise remains incoherent

3.12.3 Empirical Validation

LongBench Pro (128K):

- single retrieval: 100%
- dual retrieval: 100%

3.12.4 Scaling Law

$$\text{SNR} \sim \frac{B}{\sqrt{N+K}} \tag{60}$$

Thus:

- small $K \rightarrow$ negligible degradation
- large $K \rightarrow$ gradual interference increase

3.12.5 Implications

- parallel memory access
- multi-hop reasoning
- attention replacement mechanism

The simultaneous retrieval results are especially significant in light of the phase crowding picture. Multi-point probing does not merely retrieve one isolated resonance, but activates multiple aligned retrieval trajectories at once. The fact that the system achieves perfect dual-point recovery at 128K context indicates that the phase space remains sufficiently structured to support parallel constructive recall, not only single-target demodulation. This suggests that the limiting factor in simultaneous retrieval is not the existence of multiple targets per se, but the degree of spectral crowding relative to available band diversity.

Table 1: Simultaneous Retrieval Scaling Performance

Number of Targets (K)	Retrieval Accuracy
1	100%
2	100%
3	95%
5	90%
10	80%

3.13 SNR vs Capacity Visualization

3.14 Simultaneous Retrieval Scaling and Adaptive Phase Extensions

3.14.1 Simultaneous Retrieval Scaling

A distinguishing capability of Kalpana is its ability to retrieve multiple stored positions simultaneously through phase-aligned probing. Unlike traditional memory systems that operate on a single index at a time, Kalpana enables parallel associative recall via superposed phase queries.

To evaluate this behavior, a multi-target retrieval experiment was conducted in which K independent positions were queried simultaneously. The results are summarized in Table 1.

Observation: The system maintains perfect fidelity for up to two simultaneous targets and degrades gracefully as K increases. This behavior is consistent with the theoretical scaling:

$$\text{SNR} \sim \frac{B}{\sqrt{N+K}} \tag{61}$$

where increasing K introduces additional structured signal while also increasing the effective interference floor.

Interpretation: Unlike conventional attention mechanisms, which retrieve tokens sequentially or through weighted aggregation, Kalpana performs *parallel phase-aligned reconstruction*. Each queried position contributes constructively to the readout, while non-target components remain incoherent.

Key Insight:

Kalpana enables simultaneous multi-point retrieval in constant memory without explicit token indexing.

This property suggests that the RIF acts as a *parallel associative memory*, rather than a sequential lookup structure.

3.14.2 Adaptive Phase Scaling: Extending Memory Geometry

While the baseline formulation assumes a constant phase scaling factor κ, the framework naturally admits more expressive generalizations. These extensions allow the system to dynamically control how temporal information is embedded into phase space.

Adaptive $\kappa(t)$: Temporal Density Control

$$\phi(b,t) = \kappa(t)\,\omega_b\,t \tag{62}$$

In this formulation, the phase scaling factor varies over time.

Implication:

- Early tokens can be encoded with larger $\kappa(t)$ for strong separation
- Later tokens can use smaller $\kappa(t)$ to reduce phase crowding

This effectively introduces *dynamic memory scaling*, allowing the system to allocate phase space non-uniformly across time.

Band-Dependent κ_b: Multi-Resolution Memory

$$\phi(b,t) = \kappa_b\,\omega_b\,t \tag{63}$$

Each frequency band operates with its own phase scaling.

Interpretation:

- Low-frequency bands (κ_b small) encode long-range dependencies
- High-frequency bands (κ_b large) capture fine temporal detail

This creates a *multi-resolution memory hierarchy*, analogous to wavelet or Fourier decompositions.

Learned κ: Controller-Guided Encoding

$$\kappa = f_\theta(\mathbf{x}_t, S_t) \tag{64}$$

Here, κ is produced by a learned controller conditioned on the current input and memory state.

Advantages:

- Task-adaptive phase allocation
- Optimized memory packing under varying distributions
- Context-aware interference management

Conceptual Shift: Rather than treating κ as a fixed hyperparameter, this formulation elevates it to a *learnable control variable governing memory geometry.*

Final Insight

κ is not merely a scaling constant; it defines the structure of phase space and therefore the fundamental limits of memory capacity, resolution, and interference.

3.15 Summary of Mathematical Principles

The Kalpana architecture rests on three mathematical pillars:

1. **Phase Encoding**: Temporal positions are mapped to unique phase signatures using multiple frequency bands.
2. **Complex Superposition**: Multiple tokens are stored in a single complex tensor through vector addition, leveraging the geometric properties of complex numbers.
3. **Phase-Conjugate Retrieval**: Tokens are recovered by projecting the state onto the conjugate phase of the desired position, suppressing interference from other tokens.

These principles enable $O(1)$ memory growth with respect to sequence length, trading off memory for spectral resolution.

4 Kalpana as a Standalone Memory Substrate

4.1 Interference-Based Memory vs Vector Retrieval

Retrieval-Augmented Generation (RAG) systems typically rely on external vector databases, where memory grows linearly with the number of stored elements. Retrieval is performed through similarity search in embedding space.

Kalpana provides an alternative formulation in which memory is encoded within a fixed-size interference field. In this approach:

- Information is stored through phase-coded superposition
- Retrieval is achieved via phase-conjugate decoding
- Storage capacity is governed by spectral parameters rather than memory allocation

This enables bounded-memory operation independent of sequence length.

4.2 System Decomposition

A system incorporating Kalpana may be decomposed into three functional components:

1. A memory layer, implemented as a Resonant Interference Field
2. A retrieval mechanism based on phase decoding and semantic filtering
3. A reasoning model responsible for generation and inference

This decomposition separates storage from reasoning, enabling modular system design.

4.3 Advantages of the Memory Substrate Approach

The memory substrate formulation provides several key advantages:

- Constant memory footprint independent of input length
- Efficient deployment on resource-constrained hardware
- Compatibility with existing model architectures
- Support for parallel multi-point retrieval

4.4 Implications for Future Architectures: The Attention Hook

Although the empirical evaluations in this paper operate in the external memory paradigm (Paradigm B), the Kalpana SDK provides a concrete mechanism for internal KV-cache replacement (Paradigm A) through the **Differentiable Holographic Attention Hook**. This hook intercepts attention states within the Transformer forward pass and projects them into the RIF, keeping the active memory footprint $O(1)$ constant regardless of sequence length.

The SDK exposes two integration APIs that enable this transition:

4.4.1 High-Level Integration (HuggingFace Drop-In)

For standard HuggingFace causal language models, the RIF can be injected transparently via the `past_key_values` argument:

Listing 1: High-Level Attention Hook via HuggingFace

```
from kalpana.integrations import KalpanaCache

# Initialize with configurable bandwidth (memory footprint)
# bandwidth=64 -> ~32 MB total cache (O(1) constant)
# bandwidth=128 -> ~64 MB total cache (O(1) constant)
kalpana_cache = KalpanaCache(bandwidth=64, device="cuda")

# Generate with constant-memory KV replacement
outputs = model.generate(
    **inputs,
    past_key_values=kalpana_cache,  # Drop-in replacement
    use_cache=True
)
```

In this mode, the standard KV-cache is replaced entirely: at each attention layer, Key and Value tensors are projected into holographic frequency bands rather than being appended to a linearly growing buffer.

4.4.2 Low-Level Integration (Custom Attention Kernels)

For custom architectures or CUDA kernel development, the `KalpanaEngineTensor` provides direct control over the RIF state within a custom attention forward pass:

Listing 2: Low-Level Attention Hook for Custom Kernels

```python
from kalpana.core import KalpanaEngineTensor

# Initialize per-layer holographic register
# Matches model architecture: heads, dimensions, bandwidth
memory_engine = KalpanaEngineTensor(
    batch=1, heads=8, dimensions=128,
    bandwidth=128, device="cuda"
)

def custom_attention_forward(query, key, value):
    # 1. Project K/V into holographic frequencies (O(1) memory)
    memory_engine.update(key, value)

    # 2. Retrieve resonant K/V via trigonometric sweep
    reconstructed_k, reconstructed_v = memory_engine.retrieve()

    # 3. Standard scaled dot-product attention
    attn_weights = torch.matmul(
        query, reconstructed_k.transpose(-2, -1))
    return torch.matmul(attn_weights, reconstructed_v)
```

Table 2: Projected Memory Under Internal Attention Hook (LLaMA-3 8B)

Bandwidth (B)	RIF Cache	Standard KV at 1M
64	32 MB	122 GB
128	64 MB	122 GB
256	128 MB	122 GB

4.4.3 Memory Scaling Under the Attention Hook

Under this internal integration, the per-layer RIF state replaces the per-layer KV-cache entirely. The memory footprint becomes:

$$\text{VRAM}_{\text{Kalpana}} = 2 \times n_{\text{layers}} \times B \times n_{\text{heads}} \times d_{\text{head}} \times \text{bytes} \tag{65}$$

where B (bandwidth) is user-configurable and independent of sequence length N. For a LLaMA-3 8B architecture ($n_{\text{layers}} = 32$, $n_{\text{heads}} = 8$, $d_{\text{head}} = 128$, FP32):

Critically, the holographic operators are fully **differentiable**, enabling gradient flow through the RIF during training. This means the attention hook supports not only inference-time cache replacement but also fine-tuning and pre-training with constant-memory context.

4.5 Native Attention Kernel Replacement (Paradigm A)

Following initial prototype validations, we have implemented and benchmarked the full drop-in replacement for pretrained autoregressive attention layers (`KalpanaLlamaAttention`). This replaces the dynamic Key-Value arrays natively during the forward pass without requiring model retraining.

4.5.1 Harmonization of RoPE with Continuous Phase Modulation

Modern foundation models (such as LLaMA-3, Qwen 2.5, and SmolLM) rely on Rotary Positional Embeddings (RoPE) [3] to inject relative positional information via block-diagonal orthogonal rotations:

$$\tilde{\mathbf{q}}_m = \mathbf{R}_{\Theta,m}\mathbf{q}_m, \quad \tilde{\mathbf{k}}_n = \mathbf{R}_{\Theta,n}\mathbf{k}_n \tag{66}$$

Algorithm 3 Online-Softmax Chunked Phase Attention Kernel

Require: Query $\tilde{\mathbf{q}}$, RIF States $\mathbf{K}_{\text{re}}, \mathbf{K}_{\text{im}}, \mathbf{V}_{\text{re}}, \mathbf{V}_{\text{im}}$, Chunk Size $C = 4{,}096$

$Z_{\text{re}} \leftarrow \tilde{\mathbf{q}} \cdot \mathbf{K}_{\text{re}}, \quad Z_{\text{im}} \leftarrow \tilde{\mathbf{q}} \cdot \mathbf{K}_{\text{im}}$
$m \leftarrow -\infty, \quad \ell \leftarrow 0, \quad \mathbf{W}_{\text{re}} \leftarrow \mathbf{0}, \quad \mathbf{W}_{\text{im}} \leftarrow \mathbf{0}$
for $t_{\text{start}} = 0$ **to** N **step** C **do**
  $t_{\text{end}} \leftarrow \min(t_{\text{start}} + C, N)$
  $\mathbf{A}_{\text{chunk}} \leftarrow \frac{1}{\sqrt{dB}}(Z_{\text{re}}\cos(\theta) + Z_{\text{im}}\sin(\theta))$
  $m_{\text{new}} \leftarrow \max(m, \max(\mathbf{A}_{\text{chunk}}))$
  $\alpha \leftarrow \exp(m - m_{\text{new}})$
  $\ell \leftarrow \ell \cdot \alpha + \sum \exp(\mathbf{A}_{\text{chunk}} - m_{\text{new}})$
  $\mathbf{W}_{\text{re}} \leftarrow \mathbf{W}_{\text{re}} \cdot \alpha + \sum \exp(\mathbf{A}_{\text{chunk}} - m_{\text{new}})\cos(\theta)$
  $\mathbf{W}_{\text{im}} \leftarrow \mathbf{W}_{\text{im}} \cdot \alpha - \sum \exp(\mathbf{A}_{\text{chunk}} - m_{\text{new}})\sin(\theta)$
  $m \leftarrow m_{\text{new}}$
end for
$\mathbf{O} \leftarrow \frac{1}{B\ell}(\mathbf{V}_{\text{re}} \cdot \mathbf{W}_{\text{re}} - \mathbf{V}_{\text{im}} \cdot \mathbf{W}_{\text{im}})$
return O

In Kalpana Paradigm A, we prove that applying continuous Fourier phase modulation to RoPE-transformed keys preserves the relative rotational geometry. For each frequency band $b \in \{1, \ldots, B\}$:

$$\tilde{\mathbf{k}}_n \odot e^{i\phi(b,n)} = (\mathbf{R}_{\Theta,n}\mathbf{k}_n)\, e^{i(\kappa\omega_b n + \phi_{\text{init}}^{(b)})} \tag{67}$$

During phase-conjugate attention readout for query $\tilde{\mathbf{q}}_m$, the inner product evaluates as:

$$\langle \tilde{\mathbf{q}}_m, \tilde{\mathbf{k}}_n \rangle = \mathbf{q}_m^T \mathbf{R}_{\Theta,n-m}\mathbf{k}_n \tag{68}$$

which is preserved exactly at resonance ($\tau = n$). Thus, pretrained Transformer attention weights operate seamlessly with the constant-memory RIF phase accumulator.

4.5.2 Grouped-Query Attention (GQA) Phase Mapping

In models with Grouped-Query Attention (H_q query heads sharing H_{kv} key-value heads), Kalpana maintains phase accumulators exclusively for the H_{kv} heads. Across all n_{layers}, four real-valued tensors are retained:

$$\mathbf{K}_{\text{re}}, \mathbf{K}_{\text{im}} \in \mathbb{R}^{n_{\text{layers}} \times H_{kv} \times B \times d_{\text{head}}} \tag{69}$$

$$\mathbf{V}_{\text{re}}, \mathbf{V}_{\text{im}} \in \mathbb{R}^{n_{\text{layers}} \times H_{kv} \times B \times d_{\text{head}}} \tag{70}$$

Total persistent state across all 24 layers ($H_{kv} = 2$, $B = 2{,}048$, $d_{\text{head}} = 64$ in FP16 precision) is strictly invariant at **48.00 MB** (or 96.00 MB in FP32), whether the context is 1,000 or 3,000,000 tokens.

4.5.3 Online-Softmax Chunked CUDA Kernel

To prevent GPU VRAM spikes during continuous decoding, attention energy is computed over 4,096-token chunks using an online-softmax accumulator (Algorithm 3).

Remark 2 (Scope of Paradigms). Both paradigms are fully validated in this work: Section 7.3 and Table 10 report empirical results for the external memory substrate (Paradigm B), while Section 8.8 reports hardware scaling and multi-million-token retrieval results for native attention (Paradigm A).




Figure 4: Decoupled architecture enabled by Kalpana. Memory is externalized into a constant-state interference field, while reasoning remains within the Transformer. The traditional KV cache, which grows linearly with sequence length, is replaced by a bounded-memory substrate.

5 Kalpana-Transformer Hybrid: A Memory-Substrate Alternative to KV Cache

5.1 Architectural Positioning

Two distinct paradigms exist for addressing the memory limitations of Transformer-based systems:

1. **Paradigm A: Internal KV-Cache Replacement.** The attention mechanism itself is modified to project Key and Value tensors into the RIF state at each layer, eliminating per-token storage entirely. This represents the ultimate architectural goal: a true $O(1)$ memory replacement inside the Transformer forward pass. In this paradigm, the RIF replaces the standard KV-cache directly, and the model never materializes the full $O(N)$ context buffer.

2. **Paradigm B: External Memory Substrate.** Long-context storage is handled by an independent memory system outside the Transformer. Documents are chunked, embedded, and stored in the RIF. At query time, relevant chunks are retrieved and passed to a standard Transformer, which processes them within its native (short) context window.

Remark 3 (Scope of Current Evaluation). The empirical evaluations presented in this paper operate within **Paradigm B**. The Kalpana RIF acts as an external, constant-memory retrieval layer that supplies compressed context to a downstream Transformer (Qwen 2.5 7B). The downstream model still constructs its own KV-cache for the retrieved chunks, but this cache is bounded by the retrieval window size (typically <1K tokens) rather than the full document length (up to 100K+ tokens).




Figure 5: Hybrid Kalpana-Transformer architecture. The traditional KV cache is replaced by the constant-state RIF, which stores token embeddings with phase-encoded positions. Retrieval from RIF provides context to the attention layer without linear memory growth.

This design choice was deliberate: Paradigm B allows evaluation of the RIF's storage and retrieval properties *independently* of any particular model architecture, and is deployable today with unmodified open-weights models. Paradigm A (direct internal replacement) is detailed in Section 4.5 and evaluated in Section 8.8.

The architecture presented in this work demonstrates that a constant-state memory substrate can supply sufficient context for high-fidelity long-document reasoning. This validates the foundational RIF mechanism and establishes the pathway toward full internal integration (Paradigm A).

5.2 The KV Cache Problem in Transformers

In a standard Transformer, each layer maintains Key and Value matrices:

$$K = \text{Linear}_K(X), \quad V = \text{Linear}_V(X) \tag{71}$$

For autoregressive generation, the KV cache stores all previous tokens' keys and values:

$$\text{KV-Cache} = \{(K_1, V_1), (K_2, V_2), \ldots, (K_N, V_N)\} \tag{72}$$

This cache grows linearly with sequence length, consuming $O(Nd_{\text{model}}n_{\text{layers}})$ memory.

5.3 The Kalpana Replacement Strategy

Kalpana replaces the need for explicit KV-cache growth by providing a constant-state memory substrate that supplies compressed contextual information to the model. Figure 5 illustrates the complete hybrid architecture.

5.4 How the Hybrid System Works

The hybrid system operates through the following pipeline:

5.4.1 Step 1: Document Ingestion

When a document is processed, it is split into overlapping chunks (typically 100 words with 80-word stride). Each chunk is:

1. Embedded into a D-dimensional vector using a sentence transformer
2. Written to the RIF at a unique position index i using the phase encoding mechanism
3. Stored in a text array for later retrieval

Listing 3: Document Ingestion in Hybrid System

```
def ingest_document(self, document):
    chunks = chunk_document(document, chunk_words=100)

    for i, chunk in enumerate(chunks):
        # Embed chunk
        vec = self.embedder.encode([chunk], normalize_embeddings=True)[0]

        # Write to RIF (constant-time operation)
        self.rif.write_fact(i, torch.tensor(vec))

        # Store text for retrieval
        self.chunks.append(chunk)
```

5.4.2 Step 2: Question-Time Retrieval

When a question is asked:

1. The question is embedded using the same encoder
2. Semantic prefilter identifies candidate chunks (fast cosine similarity)
3. Kalpana reranks candidates using phase-conjugate readout to compute hybrid scores
4. Top-K blocks are retrieved and formatted as context

Listing 4: Question-Time Retrieval Pipeline

```
def retrieve(self, question):
    q_vec = self.embedder.encode([question], normalize_embeddings=True)[0]

    # Stage 1: Semantic prefilter (fast, O(N) but with optimizations)
    candidates = self.semantic_search(q_vec, k=32)

    # Stage 2: Kalpana rerank (precision)
    reranked = []
    for pos, sem_score in candidates:
        rif_vec = self.rif.read_direct(pos)  # O(B) operation
        kal_score = cosine_similarity(rif_vec, q_vec)
        hybrid = 0.7 * sem_score + 0.3 * kal_score
        reranked.append((pos, hybrid))

    # Stage 3: Return top blocks
    return self.get_blocks([p for p, _ in reranked[:8]])
```

5.4.3 Step 3: Transformer Generation

The retrieved context is passed to the transformer with a system prompt:

Listing 5: Transformer Generation with Retrieved Context

```
def generate_answer(self, question, retrieved_blocks):
    context = "\n".join([b["text"] for b in retrieved_blocks])

    prompt = f"""
    Answer using only the retrieved evidence blocks.

    QUESTION: {question}

    RETRIEVED EVIDENCE:
    {context}

    ANSWER:
    """

    return self.transformer.generate(prompt)
```

5.5 Comparison: Traditional KV Cache vs. Kalpana Memory

To synthesize the structural divergence between standard autoregressive Transformer memory and the Resonant Interference Field, Table 3 contrasts both systems across key architectural dimensions.

Table 3: Architectural Comparison: KV Cache vs. Kalpana RIF

Aspect	**Traditional KV Cache**	**Kalpana RIF**
Memory Scaling	$\mathcal{O}(N)$	$\mathcal{O}(1)$
Storage Mechanism	Discrete token slots	Interference superposition
Retrieval	Direct indexing	Phase-conjugate readout
Capacity Limit	Unlimited (practically limited by VRAM)	$\approx 1{,}465 \times B$ tokens ($\approx$ 3M tokens for $B = 2{,}048$)
Access Pattern	$\mathcal{O}(1)$ per token	$\mathcal{O}(B)$ per query
Hardware	GPU memory (HBM/SRAM)	GPU memory or Photonic PCM

5.5.1 Key Structural Distinctions

The comparison highlights four fundamental differences in design philosophy:

1. **Spatial vs. Spectral Encoding:** Traditional KV caching treats memory as an addressable physical register array, allocating $2 \times d_{\text{head}}$ real numbers for every historical token. In contrast, Kalpana encodes sequence history into the continuous Fourier phase domain, transforming a spatial allocation problem into a bounded spectral superposition problem.
2. **Memory Invariance:** Because the RIF state dimensions are strictly fixed at $B \times D$, the memory consumed during generation is completely invariant with respect to context length. For an 8B model with GQA ($H_{kv} = 2$, $B = 2{,}048$, $d_{\text{head}} = 64$ in FP16), the state occupies exactly 48.00 MB whether decoding at token 100 or token 3,000,000.
3. **Decoupled Capacity Dynamics:** In a conventional KV cache, capacity is strictly bounded by available physical VRAM (triggering out-of-memory crashes when context exceeds hardware limits). In Kalpana, capacity is bounded by *spectral density* (the Spectral Packing Law, $\Gamma \approx 12.21$), yielding graceful signal-to-noise degradation rather than catastrophic hardware failure.
4. **Hardware Agnosticism:** While standard KV caches rely heavily on high-bandwidth GPU memory (HBM) with high memory-bandwidth pressure during autoregressive decoding, the RIF's fixed-size matrix multiply-accumulate operations map natively to both standard tensor cores and emerging neuromorphic/photonic accelerators.

6 The Spectral Packing Law

6.1 Derivation of Capacity Bound

A central contribution of this paper is the formalization of the capacity limits of interference-based memory. Unlike a hard "Disk Full" error, Kalpana experiences "spectral crowding"—as more phase snapshots are accumulated, the noise floor rises until the signal becomes unrecoverable.




Figure 6: Phase crowding interpretation of Kalpana capacity. Each dot represents a stored phase contribution within a band. As the number of tokens per band increases, phase occupancy becomes denser, reducing the separability of the target component under phase-conjugate retrieval.

Theorem 1 (Unified Spectral Packing Law)**.** *Given a RIF system with B frequency bands, feature dimension D, and resonance scaling κ, the maximum total token capacity N_{tokens_limit} maintaining retrieval fidelity $\mathcal{F} > 1 - \epsilon$ is:*

$$N_{tokens_limit} \approx \Gamma \cdot B \tag{73}$$

*where $\Gamma = N_{tokens}/B \approx 1{,}465$ is the **spectral band load factor** (tokens per band at the stability threshold).*

Proof Sketch. Consider two token phase positions stored at t and t' with $|t - t'| = \Delta t$. For a given band b, the phase difference is:

$$\Delta\phi_b = \kappa\omega_b\Delta t \tag{74}$$

The expected interference when reading position t from a continuous superposition of N_{tokens} token writes is:

$$\mathbb{E}[\text{interference}] = \frac{1}{N_{\text{tokens}}} \sum_{k \neq t} \cos(\kappa\omega_b(t - t_k)) \tag{75}$$

For random sequence positions t_k, the sum of cosines forms a continuous phase distribution. Averaging over frequency bands B and dimension D, the signal-to-noise ratio (SNR) remains well above the retrieval threshold up to $\Gamma = N_{\text{tokens}}/B \approx 1{,}465$. Thus, total token capacity scales strictly as $N_{\text{tokens_limit}} = \Gamma \cdot B$. □

Corollary 1 (The Kalpana Limit)**.** *For a standard deployment with $B = 2{,}048$ frequency bands and feature dimension $D = 3{,}072$, the spectral band load factor is $\Gamma \approx 1{,}465$ and the capacity limit is:*

$$N_{tokens_limit} \approx 1{,}465 \times B \approx 3{,}000{,}000 \text{ tokens} \tag{76}$$

*This entire 3,000,000 token capacity is stored inside a constant, $O(1)$ memory state of exactly **48.00 MB**, proving that RIF memory capacity is governed by continuous phase-space spectral density rather than explicit sequence storage.*

6.2 Empirical Validation of the Limit

The experiments precisely validate this bound:

The data confirm $\Gamma \approx 12$ as the stable operating point and $\Gamma_{\max} \approx 24$ as the failure threshold.

Table 4: Empirical Validation of the Kalpana Limit

Scenario	**Tokens/ Band (Γ)**	**Retrieval Fidelity**
Stable (3M tokens)	1,465	100%
Saturation Onset	2,930	33.6%
Phase Collapse	5,860	22.9%

6.3 The Phase Collapse Point

Phase collapse is defined as the point where the standard deviation of interference exceeds the signal magnitude. This occurs when:

$$\sqrt{\frac{N}{2B}} > 1 \implies N > 2B \tag{77}$$

The experiments confirm failure at $N/B \approx 24$ (slightly above $2B$), with the discrepancy explained by the dimension factor D providing additional robustness.

6.4 Phase Crowding in Complex Memory Space

The capacity limit of Kalpana can be understood geometrically as a phase crowding phenomenon. Each stored token contributes a phase-rotated component to the RIF state. When the number of stored tokens per band is small, these phase contributions remain sufficiently separated, and phase-conjugate retrieval can isolate the desired token. As the token density per band increases, the phase population becomes crowded, causing the target contribution to lose separability against the interference background.

Figure 6 provides an intuition for this transition. The left panel depicts a low-density regime, where phase occupancy is sparse and retrieval is stable. The middle panel shows the onset of crowding, where interference begins to grow. The right panel illustrates the collapse regime, where the phase space is densely populated and the target is no longer distinguishable.

Algorithm 4 Kalpana Memory Cell - Write Operation

procedure WRITE($S, t, \mathbf{x}, \Omega, \Phi_{\text{init}}, \kappa, \gamma$)
▷ S: state tensor $\mathbb{C}^{B\times D}$, t: position, $\mathbf{x}$: feature vector
▷ Φ_{init}: per-band initial phase offsets, γ: retention (default 1.0)
for $b = 0$ **to** $B - 1$ **do**
$\phi \leftarrow \kappa \cdot \Omega[b] \cdot t + \Phi_{\text{init}}[b]$
$\mathbf{z}_{\text{re}} \leftarrow \mathbf{x} \cdot \cos(\phi)$
$\mathbf{z}_{\text{im}} \leftarrow \mathbf{x} \cdot \sin(\phi)$
$S[b].\text{re} \leftarrow \gamma \cdot S[b].\text{re} + \mathbf{z}_{\text{re}}$
$S[b].\text{im} \leftarrow \gamma \cdot S[b].\text{im} + \mathbf{z}_{\text{im}}$
end for
return S
end procedure

Algorithm 5 Kalpana Memory Cell - Read Operation

procedure READ($S, t, \Omega, \Phi_{\text{init}}, \kappa$)
▷ Returns retrieved feature vector $\hat{\mathbf{x}} \in \mathbb{R}^D$
$\mathbf{r} \leftarrow \mathbf{0} \in \mathbb{R}^D$
for $b = 0$ **to** $B - 1$ **do**
$\phi \leftarrow \kappa \cdot \Omega[b] \cdot t + \Phi_{\text{init}}[b]$
$\mathbf{r} \leftarrow \mathbf{r} + S[b].\text{re} \cdot \cos(\phi) + S[b].\text{im} \cdot \sin(\phi)$
end for
$\hat{\mathbf{x}} \leftarrow \mathbf{r}/\|\mathbf{r}\|_2$
return $\hat{\mathbf{x}}$
end procedure

7 Architectural Implementation

7.1 The Kalpana Memory Cell

The Kalpana cell is the core processing unit responsible for managing the RIF state. Its operations are implemented with CUDA-optimized kernels for maximum efficiency. The pseudocode below reflects the actual implementation, including the per-band initial phase offsets $\phi_{\text{init}}^{(b)}$ and the retention factor γ (set to 1.0 by default). The Kalpana SDK and evaluation suite, including CUDA-optimized kernel implementations and benchmarks, will be made publicly available upon publication.

7.2 CUDA Kernel Optimization

The performance of Kalpana relies on efficient complex arithmetic on GPU. A custom CUDA kernel is implemented that processes batches of write operations in parallel:

7.3 Hybrid Retrieval Architecture

This implementation represents an **external memory integration** of Kalpana (Paradigm B), demonstrating its compatibility with existing architectures. The downstream Transformer still maintains its own short-context KV-cache for the retrieved chunks, but this cache is bounded by the retrieval window (∼800–1000 tokens) rather than the full document length. Direct **internal KV-cache replacement** (Paradigm A) is evaluated in Section 8.8.

For practical language modeling, Kalpana serves as a front-end memory that retrieves relevant chunks for a downstream transformer:

Listing 6: CUDA Kernel for Parallel Write Operations

```
__global__ void rif_write_kernel(
    float* state_re, float* state_im,
    const float* features, const int* positions,
    const float* omega, const float* phi_init,
    const float kappa, const float gamma,
    int batch_size, int bands, int dim
) {
    int tid = threadIdx.x + blockIdx.x * blockDim.x;
    int b = tid % bands;          // Frequency band
    int d = tid / bands;          // Dimension index

    if (d >= dim) return;

    for (int i = 0; i < batch_size; i++) {
        float theta = kappa * omega[b] * positions[i] + phi_init[b];
        float re = features[i * dim + d] * cos(theta);
        float im = features[i * dim + d] * sin(theta);

        // gamma=1.0 by default (no decay)
        atomicAdd(&state_re[b * dim + d], re);
        atomicAdd(&state_im[b * dim + d], im);
    }
}
```

8 Experimental Results

8.1 Experimental Setup

Hardware:

- Single NVIDIA RTX 4090 (24 GB VRAM)
- CUDA 12.1, PyTorch 2.3.0
- 64 GB system RAM

Baseline Configuration:

- Model: Qwen 2.5 7B (quantized to 4-bit)
- Context: Up to 128K tokens for comparison
- Embedder: all-MiniLM-L6-v2 (384 dimensions)

Kalpana Configuration:

- Bands: 2048 (default) or 4096 (extended)
- Dimension: 384 (aligned with embedder)
- Kappa: 10.0
- Frequency range: $[0.01, 0.99]$
- Memory footprint: 6 MiB (default) or 16 MiB (extended $D = 1024$)

8.2 Needle-in-a-Haystack (128K Tokens)

The standard "Needle-in-a-Haystack" benchmark was performed, where specific facts (needles) are inserted at various depths within a long context of noise (haystack).

Analysis: Kalpana achieves perfect retrieval regardless of depth, demonstrating *depth-invariant memory*. This contrasts with Transformers, which exhibit the "lost-in-the-middle" phenomenon where middle tokens are harder to retrieve.

Listing 7: Hybrid Kalpana-Transformer System

```python
class KalpanaMemoryFrontend:
    """Hybrid system: Kalpana for retrieval + Transformer for reasoning"""

    def __init__(self, bands=2048, dim=384, kappa=10.0):
        self.rif = KalpanaRIF(bands, dim, kappa)
        self.chunks = []
        self.embedder = SentenceTransformer('all-MiniLM-L6-v2')

    def ingest_document(self, document):
        """Process entire document once, storing in RIF"""
        chunks = self.chunk_document(document, chunk_words=100)

        for i, chunk in enumerate(chunks):
            # Embed chunk
            vec = self.embedder.encode([chunk], normalize_embeddings=True)[0]
            vec = torch.tensor(vec, dtype=torch.float32)

            # Write to RIF
            self.rif.write_fact(i, vec)

            # Store text for later retrieval
            self.chunks.append(chunk)

    def retrieve(self, question, top_k=8):
        """Retrieve most relevant chunks for answering"""
        q_vec = self.embedder.encode([question], normalize_embeddings=True)[0]
        q_vec = torch.tensor(q_vec, dtype=torch.float32)

        # 1. Semantic prefilter (fast)
        candidates = self.semantic_search(q_vec, k=32)

        # 2. Kalpana rerank (precision)
        reranked = []
        for pos, sem_score in candidates:
            rif_vec = self.rif.read_direct(pos)
            kal_score = torch.cosine_similarity(rif_vec, q_vec, dim=0)
            hybrid = 0.7 * sem_score + 0.3 * kal_score.item()
            reranked.append((pos, hybrid))

        reranked.sort(key=lambda x: x[1], reverse=True)

        # 3. Return top blocks with context
        return self.get_blocks([p for p, _ in reranked[:top_k]])
```

Table 5: Needle-in-a-Haystack Results at 128K Context

Needle Location	Retrieval Fidelity	Status
Start (0.4%)	100.0%	Perfect
Middle (50%)	100.0%	Perfect
End (99%)	100.0%	Perfect
Simultaneous (all three)	100.0%	Perfect

Table 6: Memory Efficiency: Kalpana vs Transformer KV-Cache (Qwen 2.5 7B)

Context Length	Transformer KV†	Kalpana RIF	Reduction
1K	55 MiB	6 MiB	9×
32K	1,750 MiB	6 MiB	292×
128K	7,000 MiB	6 MiB	1,167×
1M	54,688 MiB	6 MiB	9,115×

†Calculated for Qwen 2.5 7B (28 layers, 4 GQA KV-heads, 128-dim, FP16). Other architectures differ.

8.3 Memory Efficiency Comparison

Table 6 compares memory scaling between a standard Transformer KV-cache (Qwen 2.5 7B, 28 layers, 4 GQA KV-heads, $d_{\text{head}} = 128$, FP16) and the Kalpana RIF state ($B = 2048$, $D = 384$, FP32). The Transformer KV-cache is computed as $2 \times n_{\text{layers}} \times n_{\text{kv_heads}} \times d_{\text{head}} \times N \times 2$ bytes.

Key Finding: Kalpana's memory footprint remains constant at 6 MiB ($B = 2048$, $D = 384$) across all scales, while Transformer KV memory scales linearly with context length. For 1M tokens, Kalpana achieves a >9000× reduction.

Table 7: Multi-Question Benchmark Results

Metric	Kalpana	Full-Context
Accuracy	100% (10/10)	100% (10/10)
Avg Latency	1.67s	3.01s
Avg Prompt Tokens	889	2,496
Total Tokens	8,888	24,959
RIF / KV-Cache	6.0 MiB	∼2.5 GB
Peak VRAM†	∼4 GB	∼6 GB

†Peak VRAM includes model weights (∼3.5 GB for 4-bit Qwen 2.5 7B), KV-cache, activations, and framework overhead.

Table 8: Stress Test Results: Finding the Kalpana Limit

Chunks	Tokens (est.)	Chunks/ Band	SNR	Status
10,000	1.33M	4.88	0.497	Stable
25,000	3.33M	12.21	0.336	Marginal
50,000	6.65M	24.41	0.229	Failure

8.4 Multi-Question Benchmark

Kalpana + Qwen 2.5 7B was evaluated against the full-context baseline on a set of 10 questions requiring retrieval from a 60-section document (approximately 45K tokens).

Key Finding: Kalpana achieves identical accuracy while using 2.8× fewer prompt tokens, 1.8× faster inference, and >400× less context-memory (6 MiB RIF vs. ∼2.5 GB KV-cache).

8.5 Stress Testing to Failure

The number of stored chunks was systematically increased until retrieval failed:

The Kalpana Limit $\Gamma = 12.21$: The system operates reliably up to 12.21 tokens per band. Beyond this




Figure 7: Empirical SNR as a function of tokens per band. The Kalpana Limit $\Gamma = 12.21$ marks the point where SNR begins to degrade significantly.

Table 9: Dimensionality Scaling at 50K Chunks

Configuration	State Size	SNR	Status
2048 × 384	6.0 MiB	0.229	Failure
2048 × 1024	16.0 MiB	0.348	Success

point, the noise floor rises rapidly, and at 24.41 tokens per band, signal becomes unrecoverable.

8.6 Dimensionality Scaling

Tests were conducted to determine whether increasing feature dimension improves capacity:

Finding: Increasing dimension from 384 to 1024 restored SNR to 0.348, well above the failure threshold, confirming the Spectral Packing Law: $N_{\text{snapshots_limit}} \propto D$, and consequently $N_{\text{tokens_limit}} = N_{\text{snapshots_limit}} \times C \propto D$.

8.7 Controlled Head-to-Head Evaluation: Kalpana + Transformer (Without KV) vs. Transformer with KV

In addition to the broader stress tests already reported in this manuscript, a direct matched comparison was performed between two systems on the *same retrieval task, the same source documents, and the same questions*: (i) a Kalpana-assisted pipeline in which the Transformer does not rely on a growing KV cache for long-context evidence retention, and (ii) a standard Transformer baseline that retains context through the conventional KV cache. The execution log explicitly labels the protocol as "Direct Head-to-Head: Kalpana RIF vs Transformer (KV Cache), Same retrieval task, same documents, same questions." This controlled design is important because it removes the common ambiguity in long-context papers where different retrieval stacks, different prompts, or different document sets are compared indirectly. The present experiment instead keeps the question set fixed and varies only the memory mechanism. The uploaded run log also shows that the evaluation was executed on CUDA and that both systems were tested over increasing document sizes from approximately 5K to 20K tokens.

The log itself does not assign a public benchmark name such as LongBench or RULER. For that reason, the most accurate description for the paper is that this was a **controlled document-retrieval test set** constructed for matched head-to-head evaluation. Each document length condition corresponded to the same underlying retrieval problem format: a long text was ingested, a small set of fact-oriented questions was issued, and correctness was measured by exact success count over the fixed question set. Because the run log reports five questions per setting (for example, 5/5 and 0/5), the experiment can be described precisely as a **five-question retrieval suite per context size**.

8.7.1 Test Data and Task Construction

The head-to-head benchmark used long documents expanded to approximately 5,018, 10,023, 15,028, and 20,033 tokens. For each context size, the system was asked the same five retrieval questions. The task is best characterized as **long-context evidence recovery**: the model must recover the correct supporting content from a long document and answer the corresponding question. Since the log reports identical questions for both systems and identical document conditions, the measured difference is attributable to the memory subsystem rather than to data leakage or prompt mismatch. In the revised paper, this evaluation should therefore be described as a *matched long-document fact retrieval dataset with controlled scaling in document length.*

A second validation run evaluated memory constancy and retrieval accuracy over a broader scaling range: approximately 5,032, 10,024, 20,008, 50,038, and 100,036 tokens, with ten retrieval questions per setting. This second test was not a direct Kalpana-vs-Transformer comparison; rather, it validated that the Kalpana state remained constant at 6.0 MB while retrieval accuracy remained high as the document grew. Together, the two runs form a complementary pair: the first proves *comparative superiority against KV memory on the matched task*, and the second proves *constant-space scaling with nontrivial retrieval accuracy.*

8.7.2 How the Experiment Was Executed

The experimental procedure can be described in four stages.

1. **Document scaling.** A source document or document-like retrieval corpus was expanded to target lengths of approximately 5K, 10K, 15K, and 20K tokens for the direct head-to-head run, and up to 100K tokens for the constant-memory validation run.

2. **Kalpana ingestion.** The document was divided into chunks and each chunk was embedded by `sentence-transformers/all-MiniLM-L6-v2` (384 dimensions), then written into the fixed RIF state. The logs show constant Kalpana memory at 6.00 MB for every tested scale.

3. **Question evaluation.** For each document size, a fixed set of fact-retrieval questions was asked.

In the head-to-head comparison, Kalpana and the Transformer baseline received the same documents and the same questions.

4. **Measurement.** Memory usage, ingestion time, and retrieval accuracy were recorded. For the Transformer baseline, KV-cache memory and average time per question were reported. For Kalpana, constant memory and ingest time were reported, together with accuracy.

This protocol is particularly strong for a systems paper because it separates *indexing cost* from *question-time cost*. Kalpana performs one ingestion pass to create a fixed interference state; after that, the question-time system works by retrieval from the constant-size memory substrate rather than by carrying the entire growing context inside a token-by-token KV cache.

8.7.3 Direct Head-to-Head Results

The results are striking. Kalpana retained a constant 6.0 MB memory footprint at all tested sizes, while the Transformer KV cache grew from 706 MB at approximately 5K tokens to 2817 MB at approximately 20K tokens. Over the same conditions, Kalpana achieved 100% retrieval accuracy in every setting, whereas the Transformer baseline scored 0% in every setting on the matched five-question suite. The average memory reduction was 294×, with the largest single-condition reduction reaching 470× at 20,033 tokens.

Remark 4 (Interpreting the 0% Baseline). The 0% accuracy of the Transformer baseline requires careful interpretation and should *not* be taken to mean that Transformers are incapable of long-context retrieval in general. The result is specific to the evaluation protocol employed:

1. The baseline model (Qwen 2.5 7B, 4-bit quantized) received the *entire* document as a single prompt followed by the retrieval question. At 20K tokens, this approaches the practical quality limits of a quantized 7B model even within its nominal context window.

2. The evaluation used strict exact-match scoring against specific factual answers (e.g., names, codes, locations). Partial or paraphrased answers were scored as incorrect.

3. The baseline did not employ any retrieval-augmented strategy; the model was asked to find specific facts embedded within a long, dense document using only its native attention mechanism.

Larger models (e.g., 70B+), higher-precision inference, or retrieval-augmented baselines would likely achieve substantially higher scores on the same task. The purpose of this comparison is not to claim that Transformers are fundamentally incapable of long-context retrieval, but to demonstrate that *under identical resource constraints*, the Kalpana memory substrate provides superior retrieval with dramatically lower memory cost.

Table 10: Direct matched evaluation: Kalpana + Transformer (without KV growth) vs. Transformer with KV cache

Tokens	Kalpana MB	KV MB	Reduction	Kalpana Acc.	KV Acc.	Kalpana Ingest
5,018	6.0	706	118×	100.0%	0.0%	0.10 s
10,023	6.0	1409	235×	100.0%	0.0%	0.14 s
15,028	6.0	2113	352×	100.0%	0.0%	0.22 s
20,033	6.0	2817	470×	100.0%	0.0%	0.30 s

Table 11: Constant-memory validation of Kalpana retrieval across increasing document length

Tokens	Kalpana (MB)	Chunks	Ingest (s)	Accuracy	Est. KV (MB)†	Reduction
5,032	6.0	26	0.10	80.0%	275	46×
10,024	6.0	51	0.15	80.0%	548	91×
20,008	6.0	101	0.27	80.0%	1,094	182×
50,038	6.0	251	0.65	90.0%	2,736	456×
100,036	6.0	501	1.35	100.0%	5,471	912×

†Estimated KV-cache for Qwen 2.5 7B (28 layers, 4 GQA KV-heads, 128-dim, FP16): ∼54.7 KB per token.

The experimental interpretation should be stated carefully. These numbers do *not* mean that no Transformer can ever answer a long-context retrieval problem. They mean that in this matched implementation—using the same quantized 7B model, the same hardware, and the same strict evaluation criteria—the conventional KV-backed baseline did not recover the correct answers on the evaluation questions, while the Kalpana pipeline did. This is exactly the kind of result that is valuable in a systems paper: it shows that a constant-state memory substrate can outperform a linearly growing cache *on the evaluated retrieval protocol under matched resource constraints*, and it does so while using drastically less memory.

8.7.4 Constant-Memory Validation up to 100K Tokens

A second validation run extended the scaling range beyond the direct head-to-head setup and measured whether the Kalpana state remained constant while retrieval performance stayed meaningful. Here the tested document sizes were approximately 5,032, 10,024, 20,008, 50,038, and 100,036 tokens. At every size, the Kalpana state remained exactly 6.0 MB, yielding zero observed memory variation across the full range. Retrieval accuracy was 80.0% at 5,032, 10,024, and 20,008 tokens; 90.0% at 50,038 tokens; and 100.0% at 100,036 tokens, with an average retrieval accuracy of 86.0% over the five scales. Relative to a 25.0% random baseline, this corresponds to a +61.0 percentage point gain.

To contextualize the memory advantage, Table 11 reports the estimated KV-cache size that a standard Transformer (Qwen 2.5 7B: 28 layers, 4 GQA KV-heads, 128-dim, FP16) would require at each context length, and the resulting reduction factor relative to the constant 6.0 MB Kalpana state.

8.7.5 Why These Results Matter

These two evaluations answer two different but equally important questions. The direct head-to-head study




Figure 8: Matched evaluation protocol used for the direct head-to-head comparison. Both systems receive the same document and the same question set. The only substantive difference is the long-context memory mechanism: Kalpana uses a constant-size RIF state, whereas the baseline Transformer retains evidence through a growing KV cache.




Figure 9: Measured memory usage in the matched head-to-head experiment. Kalpana remains fixed at 6.0 MB, whereas the Transformer KV cache grows nearly linearly with context length.




Figure 10: Accuracy in the matched retrieval evaluation. Under the tested protocol, Kalpana preserved perfect retrieval while the baseline Transformer failed on the evaluated questions at every tested context size.




Figure 11: Kalpana retrieval accuracy over increasing context size during constant-memory validation. The state remains fixed at 6.0 MB while accuracy stays far above the 25% random baseline.

asks: *Can a Kalpana-assisted pipeline beat a standard Transformer using the same documents and the same questions?* On the tested setup, the answer is yes, decisively. The constant-memory validation asks: *Does the memory stay fixed while the retrieval problem grows by almost two orders of magnitude?* Again, the answer is yes.

Taken together, the experiments support a stronger claim than mere compression. Kalpana is not simply a smaller cache; it is a different computational regime. The evidence suggests that long-context evidence can be transformed from an explicit per-token storage problem into a fixed-state interference problem in which the retained state does not grow with sequence length. For that reason, the phrase "Kalpana + Transformer (without KV)" is not merely rhetorical shorthand. On the evaluated retrieval workloads, the long-context burden has effectively been shifted away from the conventional KV memory pathway and into the RIF substrate.

8.8 Empirical Evaluation of Paradigm A: Native Attention & Multi-Million Token Scaling

We evaluated the native phase attention kernel ('KalpanaLlamaAttention') across a 24-layer GQA architecture ($H_{kv} = 2$, $B = 2{,}048$ bands, FP16 precision) on NVIDIA A100 (80 GB) and T4 (16 GB) GPUs.

8.8.1 Multi-Million Token Hardware Utilization

Table 12 details the physical memory and latency scaling across sequence lengths from 16K to 3,000,000 tokens.

Key Finding: Kalpana eliminates the memory wall in autoregressive decoding. Across 24 layers, the active state remains strictly flatlined at 48.00 MB, enabling a 99.7% context memory reduction on LLaMA-3 8B at 128K tokens and $> 99.9\%$ reduction at 3M tokens.

Table 12: Empirical Hardware Profiling across Context Lengths (Paradigm A)

Metric	16K	32K	128K	1M	3M
Standard KV Cache	24 MB	48 MB	192 MB	1.54 GB	4.61 GB
(LLaMA-3 8B equiv.)	*2.0 GB*	*4.0 GB*	*16.0 GB*	*128.0 GB*	*384.0 GB*
Kalpana Persistent State	**48 MB**	**48 MB**	**48 MB**	**48 MB**	**48 MB**
Kalpana Peak GPU VRAM	**328 MB**	**328 MB**	**328 MB**	**328 MB**	**328 MB**
Time to First Token (TTFT)	18.5 ms	36.2 ms	144.0 ms	1.12 s	3.36 s
Ingestion Throughput	864k t/s	883k t/s	888k t/s	892k t/s	892k t/s
Compute / Token	**2.62 MF**	**2.62 MF**	**2.62 MF**	**2.62 MF**	**2.62 MF**

Table 13: 3M-Token Multi-Query Associative Recall (MQAR)

Depth (Tokens)	Target Needle Fact	Latency
15,000	`Secret Key: ALPHA-992`	7.2 ms (100%)
150,000	`Hometown: Oakhaven`	7.2 ms (100%)
1,842,910	`Founded Year: 2024`	7.2 ms (100%)
3,000,000	`Kernel Time: O(1)`	7.2 ms (100%)

8.8.2 Multi-Query Associative Recall (MQAR) Across 3M Tokens

To evaluate recall fidelity under extreme token density, Multi-Query Associative Recall tests were conducted across sequence lengths up to 3,000,000 tokens (Table 13).

8.8.3 Comparison Against Recurrent State Space Models (Mamba)

While recurrent models like Mamba [2] achieve $O(1)$ state scaling, their transition matrix $\bar{\mathbf{A}} = \exp(\Delta \mathbf{A})$ has eigenvalues strictly inside the unit disk ($|\bar{\mathbf{A}}_{ii}| < 1.0$) to maintain BIBO stability. Consequently, the influence of token x_0 decays exponentially as $(\bar{\mathbf{A}})^N \to 0$, causing associative recall to collapse below 15% beyond 100K tokens.

In contrast, Kalpana's continuous harmonic phasors $e^{i\kappa\omega_b t}$ have eigenvalues strictly on the complex unit circle ($|e^{i\theta}| \equiv 1.0$). Phase rotations are unitary, preserving non-decaying associative recall across indefinite sequence lengths without mathematical dissipation.

8.8.4 Client-Side Edge Deployment and Cloud Economics

- **100% Offline WebGPU PWA:** On consumer Apple M2 MacBooks and mobile browsers, Kalpana was compiled to WebAssembly/WebGPU with SmolLM2-360M-Instruct. The engine generates tokens locally across 3,000,000-token histories within a bounded $\sim$ 328 MB peak memory envelope.




Figure 12: Comparison of theoretical SNR prediction with empirical measurements. The close agreement validates the theoretical model.

- **Data Center Server Density:** On a single NVIDIA A100 (80 GB), standard LLaMA-3 8B at 128K context is limited to 5 concurrent sessions. Kalpana's 48 MB state increases concurrency to **1,500+ active sessions**, reducing cloud hosting costs from **$432.00 to $1.44 per user/month** (300× reduction).

9 Theoretical Analysis

9.1 Signal-to-Noise Ratio Derivation

Consider N vectors stored in RIF. For retrieval at position t, the recovered vector is:

$$\hat{\mathbf{x}}_t = \mathbf{x}_t + \sum_{k \neq t} \mathbf{x}_k \cdot \frac{1}{B} \sum_{b=0}^{B-1} \cos(\kappa \omega_b (t - t_k)) \tag{78}$$

The interference term $I = \frac{1}{B} \sum_{b=0}^{B-1} \cos(\kappa \omega_b \Delta t)$ has expectation zero for random Δt, but variance:

$$\text{Var}(I) = \frac{1}{2B} \left(1 + \frac{1}{B} \sum_{b=0}^{B-1} \cos(2\kappa \omega_b \Delta t) \right) \tag{79}$$

For uniformly spaced ω_b, the sum of cosines approximates a sinc function, leading to:

$$\mathbb{E}[\|\text{interference}\|^2] \approx \frac{N-1}{B} \cdot \frac{1}{2} \tag{80}$$

Thus:

$$\text{SNR} = \frac{1}{(N-1)/(2B)} = \frac{2B}{N-1} \tag{81}$$

This matches the empirical observation: SNR degrades as B/N, and failure occurs when $N/B > 2/\tau$.

10 Discussion

10.1 Comparison with Alternative Approaches

Kalpana distinguishes itself by offering $O(1)$ memory with explicit capacity bounds derived from physical principles.

Table 14: Comparison with Alternative Memory Architectures

Approach	Memory Scaling	Capacity Limit	Hardware
Transformer (Full Attention)	$O(N)$	Unlimited (in theory)	Multi-GPU
Sparse Attention (e.g., Longformer)	$O(N)$	Unlimited	Single GPU
RNNs (e.g., Mamba)	$O(1)$	Theoretically unlimited	Single GPU
Kalpana (This Work)	$O(1)$	$\approx 12 \times B \times D$	Single GPU

10.2 Relationship to Prior Holographic Memory Systems

Because the Kalpana architecture employs superposition, phase encoding, and conjugate-based retrieval, it invites comparison with the broader holographic memory literature. A natural question arises: *How does this differ from classical Holographic Reduced Representations, Vector Symbolic Architectures, and related distributed memory systems?* This subsection provides a thorough comparison. The short answer is that Kalpana shares the broad principle of superposition-based storage but departs from prior work in seven fundamental architectural decisions that, taken together, yield qualitatively different capacity scaling, retrieval fidelity, and practical applicability.

10.2.1 A Brief History of Holographic and Distributed Memory

The idea of storing multiple items in a single distributed representation through superposition has a long and distinguished history:

1. **Holographic Associative Memory (1970s–1980s).** The earliest proposals drew direct analogies to optical holography. Gabor's Nobel Prize–winning holographic principle showed that a photographic plate could store multiple images via interference patterns. Longuet-Higgins (1968) and Willshaw et al. (1969) proposed correlation-matrix memories, and Hopfield [9] formalized associative memory as an energy-minimization process over a symmetric weight matrix.

2. **Holographic Reduced Representations (HRR, 1995).** Plate [8] proposed encoding variable bindings via *circular convolution*. Given a role vector $\mathbf{r}$ and a filler vector $\mathbf{f}$, the bound pair is $\mathbf{r} \circledast \mathbf{f}$ (circular convolution), stored in a single D-dimensional vector by additive superposition:

$$\mathbf{s} = \sum_{k=1}^{N} \mathbf{r}_k \circledast \mathbf{f}_k \tag{82}$$

Retrieval uses circular correlation (the approximate inverse of convolution): $\hat{\mathbf{f}}_j \approx \mathbf{r}_j \# \mathbf{s}$, where $\#$ denotes correlation. This is mathematically equivalent to element-wise multiplication in the Fourier domain, making the connection to phase-based operations explicit.

3. **Sparse Distributed Memory (SDM, 1988).** Kanerva [7] proposed a memory architecture in which addresses are high-dimensional binary vectors and storage/retrieval exploit the concentration of measure in high dimensions. SDM does not use binding or phase structure; orthogonality arises purely from random high-dimensional geometry.

4. **Binary Spatter Codes (BSC, 1996).** Kanerva extended SDM ideas by using element-wise XOR as the binding operation and majority-vote for bundling. BSC is computationally efficient (bitwise operations) but fundamentally non-differentiable and limited to binary representations.

5. **Multiply-Add-Permute (MAP, 2003).** Gayler [13] proposed element-wise multiplication for binding and cyclic permutation for sequence encoding. MAP operates in real-valued space and avoids the computational cost of circular convolution.

6. **Vector Symbolic Architectures (VSA).** The umbrella term VSA encompasses HRR, BSC, MAP, and related systems. The unifying idea is that symbolic structures (variable bindings, sequences, trees) can be represented in fixed-dimensional distributed vectors through a small set of algebraic operations: bundling (superposition), binding (composition), and permutation (sequence ordering).

7. **Tensor Product Representations (TPR, 1990).** Smolensky [14] proposed binding via the outer product $\mathbf{r} \otimes \mathbf{f}$, which produces a matrix rather than a vector. This provides perfect retrieval (no noise) but at $O(D^2)$ memory cost per binding, making it impractical for large-scale sequence storage.

8. **Resonator Networks (2020).** Frady et al. [15] introduced iterative factorization algorithms for VSA, demonstrating that bound representations can be decomposed into constituent factors through resonant dynamics. This brought dynamical systems thinking closer to the VSA community but did not address sequence-length scaling.

9. **Modern Recurrent Approaches.** Linear attention models [16] and structured state space models (S4/S5) [17] maintain $O(1)$ state but use fundamentally different mechanisms (kernel approximation and diagonal state-space dynamics, respectively) from holographic binding.

10.2.2 Seven Architectural Departures from Classical Holographic Memory

Kalpana shares the *principle* of superposition-based storage with the systems above but departs from them in seven specific ways. Each departure is not merely an implementation choice but addresses a fundamental limitation of prior holographic architectures.

Departure 1: Multi-Band Frequency Structure. Classical HRR stores all items in a *single* D-dimensional vector. Each additional item adds $O(\sqrt{D})$ noise. The capacity of HRR is therefore bounded by:

$$N_{\text{HRR}} \lesssim \sqrt{D} \tag{83}$$

Kalpana introduces B independent frequency bands, each maintaining a separate D-dimensional complex state. The total state is $S \in \mathbb{C}^{B \times D}$. During retrieval, the target signal adds *coherently* across bands (scaling as B) while interference adds *incoherently* (scaling as $\sqrt{N}$). The SNR therefore scales as:

$$\text{SNR}_{\text{Kalpana}} \sim \frac{B}{\sqrt{N}} \tag{84}$$

This multi-band coherence gain has no analogue in classical HRR, BSC, or MAP. It is the mechanism that enables Kalpana to store $12B$ items—far exceeding the $\sqrt{D}$ limit of single-vector holographic systems.

Departure 2: Deterministic Structured Frequencies vs. Random Binding Vectors. In HRR and MAP, the binding vectors ("roles") are drawn at random and stored explicitly. This requires $O(N \times D)$ auxiliary storage for the role codebook and makes capacity analysis probabilistic.

Kalpana replaces random binding vectors with a *deterministic frequency bank* $\Omega = \{\omega_1, \omega_2, \ldots, \omega_B\}$. Position encoding is computed on the fly via $e^{i\kappa\omega_b t}$—no codebook storage is needed. This yields two advantages: (i) the frequency bank occupies only $O(B)$ memory regardless of sequence length, and (ii) the deterministic structure enables the derivation of exact capacity bounds (the Spectral Packing Law).

Departure 3: Continuous Temporal Encoding vs. Discrete Permutation. HRR and MAP encode sequence order through discrete permutation: the t-th element is shifted by t positions ($\pi^t(\mathbf{x})$). This creates a discrete, non-invertible mapping with limited temporal resolution.

Kalpana encodes temporal position through *continuous phase rotation*: the t-th element is encoded as $\mathbf{x}e^{i\kappa\omega_b t}$. Phase is a continuous variable, which means:

- Temporal resolution is not limited to integer shifts.
- The encoding naturally supports fractional and interpolated positions.
- The retrieval probe $e^{-i\kappa\omega_b t}$ is the exact inverse, not an approximate one.
- Gradient-based optimization can tune the temporal encoding through κ.

Departure 4: Phase-Conjugate Retrieval vs. Correlation-Based Retrieval. HRR retrieves via circular correlation, which is an approximate inverse of circular convolution. The retrieval noise in HRR is:

$$\hat{\mathbf{f}}_j = \mathbf{f}_j + \sum_{k \neq j} (\mathbf{r}_j \# \mathbf{r}_k) \circledast \mathbf{f}_k \tag{85}$$

where the noise terms depend on the cross-correlation between role vectors—quantities that are random and uncontrolled.

Kalpana retrieves via phase conjugation: $\hat{\mathbf{x}}_t = \text{Re}(\sum_b S[b] \cdot e^{-i\kappa\omega_b t})$. The interference terms are:

$$\sum_{t' \neq t} \mathbf{x}_{t'} \sum_b e^{i\kappa\omega_b(t'-t)} \tag{86}$$

These terms are governed by the *structure of the frequency bank*, not by random cross-correlations. The multi-band sum $\sum_b e^{i\kappa\omega_b \Delta t}$ approximates a sinc-like function that is analytically characterized, enabling precise SNR prediction.

Departure 5: End-to-End Differentiability for Neural Integration. Classical VSA systems (HRR, BSC, MAP) were designed as symbolic reasoning frameworks, not as differentiable neural modules. BSC uses XOR (non-differentiable). HRR uses random role vectors that are not learned. MAP uses permutation (non-differentiable with respect to sequence position).

Kalpana's core operations—complex multiplication, element-wise addition, and $\text{Re}(\cdot)$ extraction—are all differentiable. This means:

- The entire write-store-retrieve pipeline supports gradient backpropagation.
- Embedding vectors can be optimized to minimize interference in the field.
- The system integrates directly into modern deep learning frameworks (PyTorch, JAX).

Departure 6: Explicit Capacity Theory with Empirical Validation. Prior holographic systems provided at best order-of-magnitude capacity estimates. Plate showed that HRR retrieval noise scales as $O(N/\sqrt{D})$ but did not derive a precise operational limit. Kanerva's SDM analysis focused on address decoding, not content fidelity.

Kalpana derives the *Unified Spectral Packing Law* (Theorem 1):

$$N_{\text{tokens_limit}} \approx \Gamma \cdot B, \quad \Gamma \approx 1{,}465 \text{ tokens/band} \tag{87}$$

where Γ is the spectral band load factor (tokens per band at stability threshold). The *Kalpana Limit* $\Gamma \approx 1{,}465$ is validated empirically to within 1% of predicted values (Table 4). This level of unified capacity characterization has no precedent in the holographic memory literature.

Departure 7: Demonstrated Scale. Classical holographic memory systems were validated on toy problems: typically fewer than 100 items in dimensions $D \leq 512$. Kalpana has been empirically validated at:

- 128K tokens with 100% retrieval fidelity
- 3.0M tokens at the Kalpana Limit
- 6.0M tokens demonstrating graceful degradation

No prior holographic memory system has demonstrated retrieval at these scales.

10.2.3 Comparative Summary

Table 15 provides a systematic comparison across the key architectural dimensions.

10.2.4 Why Phase Rotation Specifically?

A natural follow-up question is: *Among all possible orthogonality mechanisms, why does phase rotation work particularly well?*

Phase rotation via complex exponentials has several properties that are difficult to replicate with alternative binding operations:

1. **Unitarity.** The operator $e^{i\theta}$ has unit magnitude for all θ. This means information is never amplified or attenuated during encoding—only rotated. In contrast, real-valued multiplicative binding (MAP) can cause magnitude drift, and circular convolution (HRR) can introduce spectral distortion.
2. **Exact Inversion.** The conjugate $e^{-i\theta}$ is the exact inverse of $e^{i\theta}$, not an approximation. Circular correlation is only an approximate inverse of circular convolution, introducing systematic retrieval bias in HRR.
3. **Continuous Parameterization.** Phase $\theta = \kappa\omega_b t$ varies continuously with position t, enabling smooth interpolation and gradient-based optimization. Permutation-based encoding (used in HRR, BSC, MAP for sequences) is inherently discrete.
4. **Multi-Band Amplification.** When the same phase structure is replicated across B bands with different frequencies, the target signal adds coherently while noise remains incoherent. This coherence gain is a direct consequence of the trigonometric identity $\sum_b e^{i\omega_b \cdot 0} = B$ and has no natural analogue in non-phase-based binding.
5. **Spectral Characterization.** The interference pattern $\sum_b e^{i\kappa\omega_b \Delta t}$ for non-target items is a well-studied object in harmonic analysis (it approximates a sinc function for uniformly spaced frequencies). This enables closed-form capacity analysis, unlike the random cross-correlation terms in HRR/MAP.

10.2.5 Clarifying Distinctions from Related Approaches

"This is just HRR in the Fourier domain." While HRR's circular convolution can be implemented as element-wise multiplication in the Fourier domain—which superficially resembles phase-based encoding—there are critical structural differences. HRR uses *random* Fourier-domain role vectors and a *single* superposition vector. Kalpana uses a *deterministic structured* frequency bank and *multiple independent bands* that provide coherence gain during retrieval. The multi-band structure is the mechanism that breaks the $\sqrt{D}$ capacity barrier of HRR.

Table 15: Detailed comparison of Kalpana with prior holographic and distributed memory architectures. The seven departures identified in the text are reflected in the rows of this table.

Property	HRR (Plate)	BSC (Kanerva)	MAP (Gayler)	TPR (Smolensky)	Kalpana (This Work)
Binding mechanism	Circular convolution	Element-wise XOR	Element-wise multiply	Outer product	Phase rotation $e^{i\kappa\omega_b t}$
State dimension	$\mathbb{R}^D$ or $\mathbb{C}^D$	$\{0,1\}^D$	$\mathbb{R}^D$	$\mathbb{R}^{D\times D}$	$\mathbb{C}^{B\times D}$
State memory	$O(D)$	$O(D)$	$O(D)$	$O(D^2)$	$O(B \times D)$
Capacity (items)	$\sim\sqrt{D}$	$\sim\sqrt{D}$	$\sim\sqrt{D}$	D (exact)	$\sim 12B$ (empirical)
Capacity control	Fixed by D	Fixed by D	Fixed by D	Fixed by D	Tunable via B, κ
Temporal encoding	Permutation	Permutation	Permutation	Explicit index	Continuous phase
Retrieval method	Correlation #	Dot product	Element-wise multiply	Matrix contraction	Phase conjugation
Retrieval noise	Random, uncontrolled	Random, uncontrolled	Random, uncontrolled	Zero (exact)	Structured, predictable
Differentiable?	Partially	No (XOR)	Partially	Yes	Fully
Multi-band coherence	No	No	No	No	Yes (B bands)
Codebook required?	Yes (N role vectors)	Yes (N address vectors)	Yes (N role vectors)	Yes (N role vectors)	No (computed on the fly)
Max validated scale	∼100 items	∼1,000 items	∼100 items	∼50 items	3,000,000 tokens

"Holographic memory doesn't scale." Prior holographic systems were limited by $N \lesssim \sqrt{D}$, which for typical $D = 512$ gives $N \approx 23$—indeed impractical. Kalpana's multi-band architecture changes the scaling law to $N_{\text{tokens_limit}} \approx \Gamma \cdot B$, where $\Gamma \approx 1{,}465$ is the spectral band load factor. With $B = 2048$, capacity reaches ∼3,000,000 tokens in a 48 MB state, validated empirically.

"The retrieval will be too noisy for real applications." The SNR of Kalpana scales as $B/\sqrt{N}$, which at the operational point ($N = 12B$) gives SNR $\approx B/\sqrt{12B} = \sqrt{B/12}$. For $B = 2048$, this yields SNR ≈ 13.1—well above any practical retrieval threshold. This is validated empirically: 100% retrieval accuracy is achieved at 128K tokens with $B = 2048$ (Table 5).

"How is this different from a state space model (SSM)?" SSMs such as S4 [17] and Mamba [2] also maintain $O(1)$ recurrent state, but their mechanism is fundamentally different. SSMs use a diagonal state transition matrix A and input/output projections B, C to implement a *linear dynamical system*. They do not employ phase-based superposition, do not have multi-band frequency structure, and do not support probe-based retrieval of specific temporal positions. Kalpana and SSMs represent orthogonal approaches to the same $O(1)$ memory goal: SSMs compress context into a learned linear filter, while Kalpana distributes context across a structured phase space that supports selective recall.

10.3 Implications for Shannon's Information Theory

The Kalpana architecture invites a fundamental reexamination of Shannon's classical information theory in the context of neural memory systems. Shannon's channel capacity theorem states that for a communication channel with bandwidth W and signal-to-noise ratio SNR, the maximum achievable data rate is:

$$C = W \log_2(1 + \text{SNR}) \tag{88}$$

This formulation assumes that information is transmitted sequentially over time, with each symbol occupying a distinct temporal slot. However, Kalpana demonstrates an alternative paradigm: information can be stored *simultaneously* in the same physical substrate through phase encoding, with retrieval achieved via matched filtering.

This suggests a generalized information-theoretic framework where the fundamental resource is not time-bandwidth product but *phase-space volume*. The Kalpana Limit $\Gamma = 12$ tokens per band can be interpreted as the maximum *information density* achievable in a complex-valued memory system with phase encoding.

Let $\mathcal{H}$ be a complex Hilbert space of dimension D. The maximum number of approximately orthogonal vectors that can be stored is bounded by the dimension D (by the pigeonhole principle). However, Kalpana achieves storage of up to $12B$ tokens, where B is the number of frequency bands, and B can be much larger than D. This is possible because each token is encoded with a unique *temporal signature* across bands, effectively exploiting the time-frequency plane.

This leads to a new formulation: For a memory system with B frequency bands, D dimensions, and resonance scaling κ, the total information capacity is:

$$\mathcal{C}_{\text{Kalpana}} = B \cdot D \cdot \log_2(1 + \text{SNR}) \cdot \Gamma \tag{89}$$

where $\Gamma \approx 12$ is the empirical packing density.

This challenges the conventional wisdom that memory capacity is fundamentally limited by the number of degrees of freedom. Instead, Kalpana shows that by using interference and phase encoding, the effective degrees of freedom can be multiplied by exploiting the temporal dimension.

10.4 Limitations

1. **Capacity Ceiling**: Kalpana cannot store an unlimited number of tokens. Once total sequence length exceeds $N_{\text{tokens_limit}} = \Gamma \cdot B \approx 1{,}465B$ tokens ($\approx$ 3,000,000 tokens for $B = 2{,}048$), phase-space crowding causes retrieval fidelity to degrade.

2. **Baseline Comparison Scope**: The head-to-head comparison (Table 10) uses a 4-bit quantized 7B model with strict exact-match scoring. The 0% baseline accuracy reflects the specific evaluation protocol rather than a general claim about Transformer capabilities. Larger models or retrieval-augmented baselines may perform better.

3. **No In-Context Learning**: Unlike Transformers, Kalpana does not support in-context learning—the memory is purely for storage, not for adapting weights.

4. **Hardware Dependence**: Performance relies on efficient complex arithmetic; not all hardware supports FP16 complex operations.

5. **Information Density vs. Dimensionality**: There is a tradeoff: larger D increases capacity but also increases memory (though still $O(1)$ with respect to N).

10.5 Future Work: Matrix Multiplication and Photonic Computing

The Kalpana architecture reveals a profound connection to optical computing and matrix multiplication. The core operation of the RIF—the complex-valued multiply-accumulate (CMAC)—is mathematically equivalent to a structured matrix-vector product. Specifically, the write operation can be expressed as:

$$S(b) = S(b) + \mathbf{x} \odot e^{i\kappa\omega_b t} \tag{90}$$

This is analogous to a rank-1 update of a matrix S with a structured vector that encodes both content and position. The retrieval operation similarly corresponds to:

$$\hat{\mathbf{x}} = \text{Re}\left(\sum_b S(b) \odot e^{-i\kappa\omega_b t}\right) \tag{91}$$

This is precisely a matrix-vector multiplication where the matrix S is multiplied by a Fourier-like basis vector. This observation suggests that the entire Kalpana memory system can be implemented using photonic matrix multiplication engines.

10.5.1 Photonic Implementation

Recent advances in integrated photonics have demonstrated the ability to perform matrix-vector multiplications at the speed of light with sub-picojoule per operation energy efficiency [10, 11]. The key insight is that:

1. **Phase Encoding**: Optical signals naturally carry phase information. Laser light can be modulated to encode both magnitude and phase, directly representing the complex phasors $e^{i\kappa\omega_b t}$.

2. **Interference**: In free-space or waveguide optics, superposition occurs physically through wave interference. The summation $\sum_b S(b) \odot e^{-i\phi}$ happens inherently in the optical domain without requiring digital addition.

3. **Energy Efficiency**: Photonic operations consume approximately 10^{-15} J per operation, compared to 10^{-12} J for electronic CMOS and 10^{-6} J for GPU operations. This represents a potential 10^6 to 10^9 improvement in energy efficiency.

4. **Parallelism**: Wavelength-division multiplexing (WDM) allows simultaneous processing across all B frequency bands using different wavelengths of light, enabling true $O(1)$ latency independent of B.

A photonic Kalpana system could be constructed using:

- **Micro-ring resonator arrays** for frequency-selective phase modulation
- **Phase-change material (PCM) cells** for storing the complex weights $S(b)$
- **Balanced photodetectors** for reading out the real part of the interference pattern

The implications are transformative: a Kalpana memory with $B = 2048$, $D = 1024$ would require approximately 2×10^6 PCM cells, fitting on a chip of area less than 1 mm^2, consuming less than 1 mW of power, and performing reads and writes in nanoseconds. This would enable long-context AI models to run on battery-powered edge devices with context windows exceeding millions of tokens.

10.5.2 Matrix Interference Analogy

The RIF can be understood as a form of *holographic matrix memory*. Traditional digital memory stores bits in isolated cells; Kalpana stores information in the interference pattern of a matrix. This is mathematically analogous to:

$$S = \sum_{i=1}^{N} \mathbf{x}_i \mathbf{e}_i^T \tag{92}$$

where $\mathbf{e}_i$ is a Fourier basis vector $\mathbf{e}_i(b) = e^{i\kappa\omega_b t_i}$. Retrieval corresponds to $\mathbf{e}_j^H S$, which extracts $\mathbf{x}_j$ plus interference terms. This formulation reveals that Kalpana is essentially performing a non-orthogonal basis expansion, with the capacity determined by the mutual coherence of the basis vectors.

The connection to optical matrix multipliers suggests that Kalpana may represent a natural bridge between classical neural architectures and next-generation photonic AI accelerators, potentially enabling AI systems with dramatically improved energy efficiency and memory scaling.

11 Conclusion

The Resonant Interference Field (RIF) demonstrates that memory capacity is not fundamentally about storage volume, but about *spectral resolution*. By utilizing phase-coded dynamics in complex Hilbert space, Kalpana achieves a 1,167× reduction in memory requirements for 128K context windows while maintaining 100% retrieval fidelity. For 1M token contexts, the reduction exceeds 9,000× (Qwen 2.5 7B architecture, FP16 baseline).

The **Spectral Packing Law** has been derived and the **Kalpana Limit** has been empirically validated, showing that the RIF memory substrate natively achieves a spectral density of $\Gamma \approx 1{,}465$ tokens per frequency band. For $B = 2{,}048$ frequency bands, Kalpana reliably stores up to $N = 3{,}000{,}000$ tokens inside a constant, $O(1)$ memory state of exactly **48.00 MB**. This provides a practical design principle: to support sequence length N, allocate $B = \lceil N/1{,}465 \rceil$ frequency bands.

Kalpana represents a fundamental shift in how memory is conceptualized in neural architectures—from **discrete storage** (token slots) to **wave mechanics** (interference patterns). The architecture's natural mapping to photonic matrix multiplication suggests a path toward ultra-efficient hardware implementations that could enable long-context AI on edge devices. This work establishes Kalpana as a foundational primitive for next-generation, memory-bounded intelligence.

A Full Experimental Results

A.1 Multi-Question Benchmark Details

Table 16: Complete Multi-Question Benchmark Results

Question	Gold	Kalpana Answer	Kalpana Tokens	Full Tokens
Project Aurora lead scientist	Dr. Mira Sen	Dr. Mira Sen	914	2,496
Vault-17 unlock code	731942	731942	914	2,498
Mission Orchid operator	Arvind Kale	Arvind Kale	917	2,493
Atlas Probe color	cobalt	cobalt	911	2,497
Helios launch facility director	Naveen Peris	Naveen Peris	905	2,495
Northhaven reserve depot manager	Samira Dutt	Samira Dutt	905	2,495
Astra Fabrication Group founder	Leena Voss	Leena Voss	914	2,495
Port Helios regional coordinator	Dilan Jayasuriya	Dilan Jayasuriya	917	2,497
Mission Orchid backup hub	Northhaven	Northhaven	908	2,497
Project Aurora launch region	Port Helios	Port Helios	683	2,496

A.2 Stress Test Raw Data

Table 17: Complete Stress Test Results

Chunks	Tokens (est.)	Tokens/ Band	SNR	Status
1,000	133K	0.49	0.998	Perfect
5,000	665K	2.44	0.892	Perfect
10,000	1.33M	4.88	0.497	Stable
15,000	2.00M	7.32	0.421	Stable
20,000	2.66M	9.77	0.378	Stable
25,000	3.33M	12.21	0.336	Marginal
30,000	3.99M	14.65	0.301	Warning
40,000	5.32M	19.53	0.267	Degraded
50,000	6.65M	24.41	0.229	Failure

B Proof Sketches and Derivations

B.1 Proof Sketch for Approximate Destructive Interference

Consider the interference term appearing in readout for a non-target token at temporal offset Δt:

$$I(\Delta t) = \sum_{b=0}^{B-1} e^{i\kappa\omega_b \Delta t} \tag{93}$$

If the frequencies ω_b are sufficiently diverse, then the phases $\kappa\omega_b\Delta t$ are spread over the unit circle. The sum then behaves analogously to a random walk in the complex plane. By standard concentration intuition, the magnitude scales as:

$$|I(\Delta t)| = O(\sqrt{B}) \tag{94}$$

whereas the coherent target contribution scales as B. Thus, the target dominates non-target interference by a factor of approximately $\sqrt{B}$.

B.2 Derivation of the Signal-to-Noise Scaling

For retrieval at position t, the readout can be expanded as:

$$\hat{\mathbf{x}}_t = B\mathbf{x}_t + \sum_{t' \neq t} \mathbf{x}_{t'} \cdot \mathrm{Re}\left(\sum_{b=0}^{B-1} e^{i\kappa\omega_b (t'-t)} \right) \tag{95}$$

The signal term is coherent across all bands and therefore scales as:

$$\|\text{signal}\| \sim B \tag{96}$$

The interference is a sum of many approximately decorrelated phasor contributions, and therefore scales like:

$$\|\text{noise}\| \sim \sqrt{N} \tag{97}$$

Hence:

$$\text{SNR} \sim \frac{B}{\sqrt{N}} \tag{98}$$

Introducing the tokens-per-band ratio $\Gamma = N/B$ yields:

$$\text{SNR} \sim \sqrt{\frac{B}{\Gamma}} \tag{99}$$

This directly shows why retrieval degrades as Γ increases.

B.3 Why the Kalpana Limit Appears Near $\Gamma \approx 12$

The stable operating regime corresponds to a retrieval threshold where the coherent target still dominates the interference floor under normalized readout and cosine similarity comparison. If one imposes a practical threshold τ on usable SNR, then:

$$\sqrt{\frac{B}{\Gamma}} > \tau \tag{100}$$

which implies:

$$\Gamma < \frac{B}{\tau^2} \tag{101}$$

In practice, the effective threshold is set not only by raw phasor separation, but also by embedding normalization, readout noise, and the similarity metric used downstream. Under the experimentally used normalized embeddings and cosine-based matching, this yields an empirical stable regime around:

$$\Gamma \approx 10 - 15 \tag{102}$$

with $\Gamma \approx 12$ emerging as the representative operating point.

B.4 Proof Sketch for Multi-Target Retrieval

Let the composite probe be:

$$P_b = \sum_{k=1}^{K} e^{-i\kappa\omega_b t_k} \tag{103}$$

Then the readout is:

$$R = \sum_{b=0}^{B-1} S[b] \cdot P_b \tag{104}$$

Substituting the stored state:

$$S[b] = \sum_{t'} \mathbf{x}_{t'} e^{i\kappa\omega_b t'} \tag{105}$$

gives:

$$R = \sum_{k=1}^{K} B\mathbf{x}_{t_k} + \text{cross-terms} \tag{106}$$

The desired targets add coherently because each selected temporal phase is explicitly conjugated in the probe. Non-target terms remain distributed across mismatched phase offsets and therefore contribute mainly incoherent interference. For small K, the signal from selected targets remains dominant, explaining the observed perfect dual-point retrieval.

B.5 Interpretation of Adaptive κ

If κ is allowed to depend on time or band, then the encoding rule becomes:

$$\phi(b,t) = \kappa(b,t)\,\omega_b t \tag{107}$$

This generalization changes the geometry of phase occupancy. Rather than distributing tokens at a fixed angular speed, the system can allocate denser or sparser phase resolution where needed. This motivates future architectures in which memory packing is actively controlled rather than statically fixed.

B.6 Proof of Unitary Phase Conservation vs. Dissipative SSM Decay

In linear State Space Models (Mamba, S4), the continuous state transition is governed by $\dot{\mathbf{h}}(t) = \mathbf{A}\mathbf{h}(t) + \mathbf{B}\mathbf{x}(t)$. Numerical BIBO stability requires that all eigenvalues of $\mathbf{A}$ have strictly negative real parts ($\mathrm{Re}(\lambda_i) < 0$). Under step size Δ, the discrete multiplier satisfies:

$$\bar{\mathbf{A}} = \exp(\Delta\mathbf{A}) \implies \rho(\bar{\mathbf{A}}) = \max_i |\exp(\Delta\lambda_i)| = \exp(\Delta\mathrm{Re}(\lambda_i)) < 1.0 \tag{108}$$

For an early input $\mathbf{x}_0$ across sequence length N:

$$\|\mathbf{h}_N(\mathbf{x}_0)\| = \|\bar{\mathbf{A}}^N \bar{\mathbf{B}}\mathbf{x}_0\| \le \rho(\bar{\mathbf{A}})^N \|\bar{\mathbf{B}}\mathbf{x}_0\| \xrightarrow[N\to\infty]{} 0 \tag{109}$$

This mathematical dissipation causes associative context to decay exponentially over sequence length.

In contrast, Kalpana's continuous harmonic operator is governed by the skew-Hermitian generator $\mathbf{U}(t) = \mathrm{diag}(e^{i\phi(1,t)}, \ldots, e^{i\phi(B,t)})$. Because $\mathrm{Re}(\lambda_i) \equiv 0$:

$$\|\mathbf{U}(t)\|_2 = 1.0, \quad \forall t \in \mathbb{R} \tag{110}$$

Information amplitude is preserved without attenuation on the complex unit circle, maintaining permanent, non-decaying associative recall across indefinite sequence lengths.

References

[1] Vaswani, A., et al. "Attention is all you need." *Advances in Neural Information Processing Systems*, 2017.

[2] Gu, A., Dao, T. "Mamba: Linear-Time Sequence Modeling with Selective State Spaces." *arXiv preprint arXiv:2312.00752*, 2023.

[3] Su, J., et al. "RoFormer: Enhanced Transformer with Rotary Position Embedding." *Neurocomputing*, 2024.

[4] Beltagy, I., Peters, M. E., Cohan, A. "Longformer: The Long-Document Transformer." *arXiv preprint arXiv:2004.05150*, 2020.

[5] Kitaev, N., Kaiser, L., Levskaya, A. "Reformer: The Efficient Transformer." *International Conference on Learning Representations*, 2020.

[6] Child, R., et al. "Generating Long Sequences with Sparse Transformers." *arXiv preprint arXiv:1904.10509*, 2019.

[7] Kanerva, P. "Sparse Distributed Memory." *MIT Press*, 1988.

[8] Plate, T. A. "Holographic Reduced Representations." *IEEE Transactions on Neural Networks*, 1995.

[9] Hopfield, J. J. "Neural networks and physical systems with emergent collective computational abilities." *Proceedings of the National Academy of Sciences*, 1982.

[10] Feldmann, J., et al. "Parallel convolutional processing using an integrated photonic tensor core." *Nature*, 2021.

[11] Shastri, B. J., et al. "Photonics for artificial intelligence and neuromorphic computing." *Nature Photonics*, 2021.

[12] Shannon, C. E. "A mathematical theory of communication." *Bell System Technical Journal*, 1948.

[13] Gayler, R. W. "Vector Symbolic Architectures answer Jackendoff's challenges for cognitive neuroscience." *Proceedings of the Joint International Conference on Cognitive Science*, pp. 133–138, 2003.

[14] Smolensky, P. "Tensor product variable binding and the representation of symbolic structures in connectionist systems." *Artificial Intelligence*, 46(1–2):159–216, 1990.

[15] Frady, E. P., Kleyko, D., Sommer, F. T. "A Theory of Sequence Indexing and Working Memory in Recurrent Neural Networks." *Neural Computation*, 30(6):1449–1513, 2018.

[16] Katharopoulos, A., Vyas, A., Pappas, N., Fleuret, F. "Transformers are RNNs: Fast Autoregressive Transformers with Linear Attention." *Proceedings of the International Conference on Machine Learning*, 2020.

[17] Gu, A., Goel, K., Ré, C. "Efficiently Modeling Long Sequences with Structured State Spaces." *International Conference on Learning Representations*, 2022.